

# CyberPower®


## Reliability. Quality. Value.

### Battery Replacement

K01-0000065-02


#### Intelligent LCD Series

MODEL: CP600LCD, CP825LCD, CP800AVR, CP685AVR-G, CP825AVR-G, CP685AVRLCD-G, CP825AVRLCD-G



1. Place the UPS on its top and remove the retaining screw (figure 1).
2. Slide the battery compartment cover completely off of the unit (figure 2).
3. Remove the battery from the compartment and disconnect the battery wires from the battery. Install the replacement battery by connecting the red wire to the positive (+) terminal and the black wire to the negative (-) terminal of the battery. (figure 3)
4. Slide the battery compartment cover over the battery and tighten the retaining screw.
5. Charge the unit for 4 – 8 hours to ensure the UPS performs expected runtimes.


MODEL: CP850AVRLCD, CP1000AVRLCD



1. Place the UPS on its side and locate the battery compartment cover on the bottom of the UPS. Remove the four (4) retaining screws and pull the battery compartment cover off the UPS (figure 1 & 2).
2. Remove the battery from the compartment and disconnect the battery wires from the batteries. Install the replacement batteries by connecting the red wire and black wire to the same color wires from the battery pack. Put the battery pack into the compartment (figure 3).
3. Slide the battery compartment cover over the battery and tighten the retaining screw. Charge the unit for 4 – 8 hours to ensure the UPS performs expected runtimes.

#### AVR Series


MODEL: CP900AVR, CP1200AVR, CP1500AVRT, CP1285AVRLCD, CP1350AVRLCD, CP1500AVRLCD



1. Place the UPS on its side to locate and remove the front panel retaining screws from the bottom of the UPS.
2. Slide the cover (front panel) towards the bottom of the UPS.
3. Remove it from the unit.
4. Disconnect the cable located at the top of the cover.
5. Disconnect the battery wires from the batteries.
6. Remove the batteries from the compartment.
7. Install the replacement batteries by connecting the red and black wires to the same color wires from the battery pack. Put the battery pack back into the compartment.
8. Replace the battery compartment cover and tighten the retaining screw. Charge the unit for 4-8 hours to ensure the UPS performs expected runtimes.

#### Smart APP Intelligent LCD Series

MODEL: OR500LCDRM1U, OR700LCDRM1U, OR1000LCDRM1U, OR1500LCDRM1U



1. Remove the right side front panel.
2. Remove the three retaining screws for the cable protection cover and remove the cover.


3. Disconnect the black and red cable.

4. Remove the one retaining screw holding the battery pack in place.

5. Remove the battery pack.

6. Install the new battery pack. Assemble the screws, cover, cable and front panel in the reverse order of the previous steps. Charge the unit for 4-8 hours to ensure the UPS performs expected runtimes.

MODEL: OR1500LCDRM2U, OR2200LCDRM2U, OR1500LCDRTXL2U, OR2200LCDRTXL2U



1. Remove the right side front panel.

2. Remove the three retaining screws for the cable protection cover and remove the cover.

3. Remove the two retaining screws from the cable connectors.


4. Disconnect the black and red cable.

5. Remove the four retaining screws holding the battery pack in place.

6. Remove the battery pack.

7. Install the new battery pack. Assemble the screws, cover, cable and front panel in the reverse order of the previous steps. Charge the unit for 4-8 hours to ensure the UPS performs expected runtimes.

MODEL: CPS1500AVR



1. Remove the right side front panel.

2. Remove the two retaining screws for the cable protection cover and remove the cover.

3. Disconnect the black and red cable.


4. Remove the four retaining screws holding the battery pack in place.

5. Remove the battery pack.

6. Install the new battery pack. Assemble the screws, cover, cable and front panel in the reverse order of the previous steps. Charge the unit for 4-8 hours to ensure the UPS performs expected runtimes.

#### Smart APP SINEWAVE Series

MODEL: PR750LCD



1. Remove the front panel of the UPS.

2. Pull out both round knobs and remove the battery compartment cover completely off of the unit.



3. Remove the batteries from the compartment.

4. Disconnect the battery wires from the batteries.


5. Install the replacement batteries by connecting the wire bundle (composed of one red wire and one black wire) to the connector from the battery pack. Put the batteries back into the compartment.

6. Re-install the battery compartment cover and push both round knobs back into place.


7. Connect to AC power and charge the new batteries for up to 16 hours to insure a full charge.

**MODEL: PR1000LCD****MODEL: PR1500LCD**


1. Remove the front panel of the UPS.  
 2. Remove two screws from the battery compartment cover and slide the cover completely off of the unit.  
 3. Remove the batteries from the compartment. Disconnect the battery wires from the batteries.  
 4. Install the replacement batteries by connecting the wire bundle (composed of one red wire and one black wire) to the connector from the battery pack.  
 5. Put the batteries back into the compartment. Re-install the battery compartment cover and tighten the retaining screws. Put the front panel back on the UPS.  
 6. Connect to AC power and charge the new batteries for up to 16 hours to insure a full charge

**MODEL: PR750LCDRM1U, PR1000LCDRM1U**


1. Remove the right side front panel.  
 2. Remove the two retaining screws for the cable protection cover and remove the cover.  
 3. Disconnect the black and red cable.  
 4. Remove the one retaining screw holding the battery pack in place.  
 5. Remove the battery pack.  
 6. Install the new battery pack. Assemble the screws, cover, cable and front panel in the reverse sequence of the above steps. Charge the unit for 4-8 hours to ensure the UPS performs expected runtimes.

**MODEL: PR1500SWRM2U, PR2200SWRM2U**


1. Remove the right side front panel.  
 2. Remove the two retaining screws for the cable protection cover and remove the cover.  
 3. Disconnect the black and red cable.  
 4. Remove the four retaining screws holding the battery pack in place.  
 5. Remove the battery pack.  
 6. Install the new battery pack. Assemble the screws, cover, cable and front panel in the reverse order of the previous steps. Charge the unit for 4-8 hours to ensure the UPS performs expected runtimes.

**MODEL: PR1000LCDRT2U, PR1000LCDRTXL2U, PR1500LCDRT2U, PR2200LCDRT2U, PR3000SWRM2U**


1. Remove the right side front panel.  
 2. Remove the three retaining screws for the cable protection cover and remove the cover.  
 3. Remove the two retaining screws from the cable connectors.  
 4. Disconnect the black and red cable.  
 5. Remove the four retaining screws holding the battery pack in place.  
 6. Remove the battery pack.  
 7. Install the new battery pack. Assemble the screws, cover, cable and front panel in the reverse order of the previous steps. Charge the unit for 4-8 hours to ensure the UPS performs expected runtimes.

**MODEL: PR1000LCDRTXL2Ua, PR1500LCDRTXL2U, PR2200LCDRTXL2U, PR3000LCDRT2U, PR3000LCDRTXL2U**

1. Remove the six retaining screws, and remove the front panel from the UPS.  
 2. Remove the two retaining screws for the cable protection cover and remove the cover.  
 3. Remove the two retaining screws from the cable connectors.  
 4. Disconnect the black and red cable.  
 5. Remove the three retaining screws holding the battery pack in place.  
 6. Remove the battery pack.  
 7. Install the new battery pack. Assemble the screws, cover, cable and front panel in the reverse order of the previous steps. Charge the unit for 4-8 hours to ensure the UPS performs expected runtimes.

**MODEL: PR5000LCDRTXL5U, PR6000LCDRTXL5U**


1. Remove the front panel.  
 2. Remove the two retaining screws of the cable protection cover and remove the cover.  
 3. Pull the plastic sticker out slowly to remove the battery module.  
 4. Put the new battery modules back into the compartment.  
 5. Tighten the screws and replace the cable protection cover and the front panel.

**PFC SINEWAVE Series****MODEL: CP850PFCLCD, CP1000PFCLCD**

1. Turn the UPS on its side. Remove the retaining screw located on the bottom of the UPS.  
 2. Slide the battery compartment cover completely off of the unit.  
 3. Remove the batteries from the compartment.  
 4. Disconnect the battery wires from the batteries.  
 5. Install the replacement batteries by connecting the red wire (+) and black wire (-) to the same color connectors from the battery pack. Put the batteries back into the compartment.  
 6. Slide back the battery compartment cover and tighten the retaining screw. Recharge the UPS


for 8-16 hours to fully charge the battery.

**MODEL: CP1350PFCLCD**




1. Turn the UPS on its side. Remove the front panel retaining screws located on the bottom of the UPS.
2. Slide the battery compartment cover (front panel) completely off of the unit.
3. Remove the batteries from the compartment.
4. Disconnect the battery wires from the batteries.
5. Install the replacement batteries by connecting the red wire (+) and black wire (-) to the same color connectors from the battery pack. Put the batteries back into the compartment.
6. Slide back the battery compartment cover and tighten the retaining screws. Recharge the UPS for 8-16 hours to fully charge the battery.

**MODEL: CP1500PFCLCD**



1. Turn the UPS on its side. Remove the front panel retaining screws located on the bottom of the UPS.
2. Slide the battery compartment cover (front panel) completely off of the unit.
3. Remove the batteries from the compartment.
4. Disconnect the battery wires from the batteries.
5. Install the replacement batteries by connecting the wire bundle (composed of one red wire and one black wire) to the connector from the battery pack. Put the batteries back into the compartment.
6. Slide back the battery compartment cover and tighten the retaining screws. Recharge the UPS for 8-16 hours to fully charge the battery.

**MODEL: OR1500PFCRT2U, OR2200PFCRT2U**



1. Remove the right side front panel.
2. Remove the three retaining screws for the cable protection cover and remove the cover.
3. Remove the two retaining screws from the cable connectors.
4. Disconnect the black and red cable.
5. Remove the four retaining screws holding the battery pack in place.
6. Remove the battery pack.
7. Install the new battery pack. Assemble the screws, cover, cable and front panel in the reverse order of the previous steps. Charge the unit for 4-8 hours to ensure the UPS performs expected runtimes.