

NUVO

Wireless Subwoofer Kit

A good sound experience could be a great one with the addition of a Nuvo powered subwoofer. However, getting a wire to right place isn't always so simple. That's why we've made it easy to add a subwoofer to almost any room with the Nuvo Wireless Subwoofer Kit.

The kit features a transmitter as well as a receiver. Connect the transmitter to your source, such as the subwoofer output of a surround receiver; and then connect the receiver to your powered subwoofer. Simply pair them and you're done.



- Easily add a Nuvo powered subwoofer to almost any system wirelessly
- Receiver is conveniently powered via USB when used with Nuvo powered subwoofers
- Automatic frequency-hopping if interference is detected
- Connect up to four wireless subwoofers to one transmitter with the addition of NV-SUBRX-xx receivers
- Wireless connection allows freedom of placement choice for the best sound
- Two year warranty
- Latency of less than 20 milliseconds

Offering maximum versatility, the wireless kit uses the relatively less-used 5GHz frequency range and will automatically hop to a new frequency if interference happens to be detected. Up to four receivers (NV-SUBRX-xx is available separately) can be connected to one transmitter. Yes, that means you can have up to four powered subwoofers wirelessly connected to one surround receiver. That seems a little extreme to us, but who are we to judge? The convenient USB jack on Nuvo subwoofers can power the wireless receiver with the supplied USB power cable or you can use the included power adapter. The wireless transmitter includes a power adapter. With a range of up to 50 feet, simple set up, placement flexibility and reliable connectivity, the NV-SUBTXRX-xx kit might just be easier than pulling a wire.



NV-SUBTX



NV-SUBRX

Nuvo NV-SUBTXRX Wireless Subwoofer Kit

Material

Painted plastic case

Output

Line Output Connector	RCA analog (single) on Receiver
Line Output Level	Same as input
Line Output Impedance	100Ohms
Signal to Noise Ratio	>83dB
Frequency	10Hz - 500Hz

Input

Line Input Connector	LFE / RCA analog (pair) on Transmitter
Input Voltage	110v - 220v (varies based on region)
Line Input Impedance	8k Ohms
Line Input Overload	2 volts
Power Supply	Varies based on region
Power Consumption (max)	10 watts
Power Consumption (typical)	5 watts
Operating Temperature	5-35° C / 41-95° F
Humidity	70% non-condensing

Operating Frequency

5.2GHz and 5.8GHz

Channel Width

<22MHz

Latency

<20 milliseconds

Transmitter Output

0dB

Modulation System

5GHz Frequency Hopping
QPSK digital ratio (DSSS)

Regulatory Approvals

cTUVus, CE-LVD
US:FCC CFR Title 47 Part 15, Subpart B; CANADA:ICES-003
EUROPE:CISPR32; EUROPE: EN 55032:2012;
AUSTRALIA/NEW ZEALAND: RCM Standard AS/NZS CISPR32
RoHS (Restriction of Hazardous Substances Directive 2002/95/EC)

Weight

Unit Weight (kg)	0.23 kg
Unit Weight (lbs)	0.5 lbs
Shipping Weight (kg)	0.5 kg
Shipping Weight (lbs)	1.1 lbs

Transmitter Size

Unit Size (mm)	33 L x 89 W x 89 H
Unit Size (inch)	1.3 L x 3.5 W x 3.5 H

Transmitter Size without feet

Unit Size (mm)	28 L x 89 W x 89 H
Unit Size (inch)	1.1 L x 3.5 W x 3.5 H

Receiver Size

Unit Size (mm)	33 L x 58 W x 89 H
Unit Size (inch)	1.3 L x 2.3 W x 3.5 H

Receiver Size without feet

Unit Size (mm)	28 L x 58 W x 89 H
Unit Size (inch)	1.1 L x 2.3 W x 3.5 H

Shipping Specifications

Unit Size (mm)	49.3 L x 248 W x 229 H
Unit Size (inch)	1.94 L x 9.75 W x 9 H

Legrand reserves the right to change specifications without notice.



designed to be better™

legrand® | AV

Legrand, North America

3015 Kustom Drive
Hebron, KY 41048
United States
844.334.8044
www.legrand.us/nuvo