



Audio Distribution Accessories



*PDM-1
Phone/Doorbell
Module*



*RSP-1
Remote Source
Wall Plate*



*RSO-1
Digital to Analog Audio Converter*



*CP-16i
16 Channel 100W Cool Power® Audio Amplifier*

AD-16x

16x16 Audio Matrix Switch

Wherever you go - let the music move with you.

Ideal for large, multi-zone audio installations, the AD-16x provides routing for 16 audio sources to 16 zones, while RTI's Cool Power® amplifier CP-16i drives crystal clear audio to every speaker. For added convenience, the AD-16x also features eight remote source inputs, which allows devices located in other rooms to be used as a global source. If the system grows past 16 zones, up to four AD-16x units can be cascaded for up to 64 output zones.* The switch also delivers complete audio management, including parametric equalizing, zone grouping, and balance control — all configurable via a convenient web interface.

Setting the AD-16x apart is the engineering that enables this matrix to become an extension of the RTI ecosystem. At the heart of this powerful integration is the AD64 two-way driver running on an RTI XP processor, providing integrators with unmatched flexibility and programming efficiency. The driver features custom project labeling, allowing integrators to name all of the zones and sources, eliminating tedious programming by ID number. Pushing the user experience to new levels, the driver also allows dynamic audio source management, which tracks the active sources. This allows a user to determine if a source is already in use and select a different one to avoid an inadvertent music change.

Key Features

- Provides routing of 16 stereo audio sources to 16 zones.
- Eight remote source inputs allow devices located in other rooms to be used as a global source using the RSP-1 accessory.
- RSO-1 digital to analog converter (sold separately) provides audio input for digital audio sources.
- Up to four AD-16x units may be source-looped, for up to 64 output zones.*
- Custom project labeling allows integrators to name all of the zones and sources for more efficient programming (via AD64 driver).
- Dynamic audio source management tracks the sources that are active, allowing users to select a different one and avoid inadvertent music changes (via AD64 driver).
- Preamp outputs require external amplification via RTI or third-party audio amplifier.
- Eight bands of parametric audio equalizing in all zones.
- Built-in web interface allows zones to be configured and grouped, allowing multiple outputs to be controlled as a single zone.
- Audio input trim adjustment on each source.

Specifications

AC Input Voltage.....	100VAC ~ 240VAC, 50~60Hz Switching Power Supply, 20W
Power Switch	Front Panel On/Off with LED
Mounting.....	Rack mount or free standing
Dimensions (W x H x D).....	16.9" (430mm) x 5.3" (133mm) x 14.5" (369mm)
Weight	14.5lb (6.6kg)
Operating Temperature.....	32°F - 104°F (0°C - 40°C)
Operating Humidity.....	5% to 95% Non-Condensing
Heat Output.....	68 BTU/hr
Output Zones.....	Sixteen zones of stereo L/R
.....	16 RCA jack pairs (switchable between fixed or variable)
Audio Source Inputs (Local)	Sixteen, 16 RCA jack pairs
Audio Source Inputs (Remote)	Eight, RJ-45 jacks
Loop Outputs.....	Sixteen, 16 RCA jack pairs
Control Input (CTRL IN).....	One, 3.5mm jack
.....	Compatible with industry standard IR repeaters and receivers
Control Output (CTRL OUT).....	One, 3.5mm jack
.....	Compatible with industry standard IR repeaters and receivers
Remote Source IR Inputs	Nine, 3.5mm jacks
.....	Eight discrete, One universal (All)
Mute Input.....	One, 3.5mm jack
.....	Phone Input Sensitivity: AC25V-AC100V 20Hz
.....	Doorbell Sensitivity: AC/DC 3-12VDC
Trigger Output (Status Jack).....	One, 12VDC, 15mA max
+12VDC Voltage Output	One, 12VDC, 500mA max
Serial (RS-232) Port.....	One, Bi-directional DB9
Ethernet Port	One, 10/100Base-T, RJ45 Connection
Unit ID Numbers.....	1-8, Set using 3 switches
Total Harmonic Distortion	<0.03%
S/N Rating	92dB (@ mute +1) , 100dB(@ mute)
Frequency Response.....	20Hz ~ 20KHz +/- 0.5 dB
Input Overload.....	2.1V
Input Impedance.....	22K ohms
Channel Separation @1KHz	>60dB
Crosstalk Between Sources	>90dB
Crosstalk Between Zones	90dB
Treble Control @10KHz.....	8.5dB +/- 0.5 dB
Bass Control Range @100Hz	8.5dB +/- 0.5 dB
Equalizer Bands (8).....	32Hz, 64Hz, 256Hz, 512Hz, 1024Hz, 2048Hz, 4096Hz, 16380Hz
Warranty	One Year (parts & labor)

All features and specifications subject to change without notice

*NOTE: Up to eight AD-16x units may be used to reach 128 output zones using Infrared control. There is a limit of four AD-16x units when the AD64 two-way driver is used, for a maximum of 64 output zones.



Rear View

Remote Technologies Incorporated

5775 12th Avenue East, Suite 180, Shakopee, MN 55379
PH: (952) 253-3100 • Website: www.rticorp.com

RTI User Interfaces

Remote Controls
Keypads
Audio Control Keypads

In-Wall Touchpanels
Tabletop Touchpanels
Mobile Apps



RTI Control Accessories

Control Processors
System Kits
RS-232 Modules

IR Modules
Relay Modules
Z-Wave Modules



RTI Audio/Video Distribution

HDMI Splitters & Switches
HDMI Matrix Switches
HDBaseT Matrix Switches

HDBaseT Extenders
Presentation Switches
Video over IP Transceivers



It's Under Control®