

TOWER CASE

Professional Series Mid-Tower Case

ATX8300PRO2
ATX8300PRO2B

Instruction Guide



* Actual product may vary from photo
* ATX8300PRO2 shown

Technical Support

The following technical resources are available for this StarTech.com product:

On-line help:

We are constantly adding new information to the *Tech Support* section of our web site. To access this page, click the *Tech Support* link on our homepage, www.startech.com. In the tech support section there are a number of options that can provide assistance with this card.

Knowledge Base - This tool allows you to search for answers to common issues using key words that describe the product and your issue.

FAQ - This tool provides quick answers to the top questions asked by our customers.

Downloads - This selection takes you to our driver download page where you can find the latest drivers for this product.

Call StarTech.com tech support for help:

USA/Canada: 1-519-455-4931

UK/Ireland/Europe: 00-800-7827-8324

Support hours: Monday to Friday 9:00AM to 5:00PM EST (except holidays)

Warranty Information

This product is backed by a two-year warranty. In addition, StarTech.com warrants its products against defects in materials and workmanship for the periods noted below, following the initial date of purchase. During this period, the products may be returned for repair, or replacement with equivalent products at our discretion. The warranty covers parts and labor costs only. StarTech.com does not warrant its products from defects or damages arising from misuse, abuse, alteration, or normal wear and tear.

Limitation of Liability

In no event shall the liability of StarTech.com Ltd. and StarTech.com USA LLP (or their officers, directors, employees or agents) for any damages (whether direct or indirect, special, punitive, incidental, consequential, or otherwise), loss of profits, loss of business, or any pecuniary loss, arising out of or related to the use of the product exceed the actual price paid for the product.

Some states do not allow the exclusion or limitation of incidental or consequential damages. If such laws apply, the limitations or exclusions contained in this statement may not apply to you.

Technical Specifications

Dimensions	18.9 (l) x 7.5 (w) x 16.4 (h) in.
Weight	17.25 lbs.
Power Supply	300 Watt 12V ATX
Power Supply Connectors	5 x 4-pin LP4 female 2 x small internal power 1 x 20-pin ATX motherboard adapter 1 x 4-pin extended ATX power 12V 1 x Aux plug for Pentium 4
Power Supply Certification	CSA, UL, FCC, CE, TUV
Motherboards Accepted	12.0 x 9.6 in. Standard ATX (including P4)
Expansion slots	Seven
Bays	Four external 5.25" Two external 3.5" Two internal 3.5"

Table of Contents

Introduction	2
Assembling Your Computer	3
Enhancing Your Tower Case	7
Technical Specifications	8
Technical Support	9
Warranty Information	9

Introduction

Thank you for purchasing a StarTech.com professional series mid-tower computer case. The convenient screwless design allows you to build and update your computer system with ease. With a total of four 5.25" and four 3.5" drive bays, there is ample room to expand and customize your system to suit your needs. This case includes a reliable StarTech.com 300 Watt Pentium 4-compliant ATX 12V power supply and front-mounted USB 2.0, FireWire, and audio ports for ultimate convenience and useability.

Features

- Allows easy access for building and upgrading your PC through screwless design
- Provides four external 5.25" drive bays, two external 3.5" drive bays, and two internal 3.5" drive bays to allow for system customization
- Includes reliable StarTech.com 300 Watt 12V ATX power supply
- Provides front USB 2.0, FireWire, and audio ports for maximum ease of use
- Comes with built-in case fan and large front-panel vents to ensure peak performance and stable operation
- Backed by StarTech.com's two-year warranty

Before You Begin

To ensure a quick and easy case assembly, please read through this section carefully before attempting to assemble your computer.

WARNING: Do not attempt to install any computer components with the system plugged in. **Never open your computer case when your system is turned on. Always make sure that the computer is off and unplugged before attempting to assemble or alter your computer.** Computer equipment can also be severely damaged by static electricity. Be sure that you are properly grounded before opening your computer case or touching any components. StarTech.com recommends that you wear an anti-static strap when installing any computer equipment. If an anti-static strap is unavailable, discharge yourself of any static electricity build-up by touching a large grounded metal surface (such as the computer case) for several seconds. Also be careful to handle cards and motherboards by their edges and not the gold connectors.

Enhancing Your Tower Case

You can increase the performance and security of your StarTech.com ATX83000PRO2 or ATX8300PRO2B with additional products from StarTech.com. Visit our website for more details and purchasing information.

Installing a Hard Drive Shock Absorber Kit

The hard drive shock kit (StarTech.com ID: 8300SHOCKKIT) is an excellent way to extend the life of your hard drive. The rubber buffers reduce the system vibrations caused by high RPM drives. This kit is also ideal for people who have to frequently move their PCs.

NOTE: For detailed instructions on how to install a hard disk drive, see "Installing a Hard Disk Drive" on page 5.

1. Ease the rubber buffer into the holes on the hard disk bracket. Make sure that the buffer is visible on both sides of the bracket.
2. Place the metal button concave-side-up (so that it looks like a bowl) against the buffer on the outside of the bracket.
3. Insert a screw through the button, buffer, and bracket to attach the bracket to the hard drive. Repeat for the three other holes.

Installing an Extra 3.5" Drive Bay

With the StarTech.com 8300HDDKIT, you can add two extra 3.5" drive bays to your system without increasing the case size.

1. Separate the bracket from the stand by lifting the black tab and sliding the bracket away from the stand.
2. With your system turned off, unplugged, and standing upright, remove the side panel.
3. Slide the tabs on the stand into the two slots on the bottom of the case.
4. Make sure that the holes in the stand are aligned with the holes in the bottom of the case and use the screw to attach the stand to the case, with the head of the screws being on the outside of the case.
5. Use the instructions on pages 4 and 5 in this manual to install your drives to the bracket.

Using the Front FireWire and Audio Ports

1. Make sure that your computer is equipped with a FireWire card and a sound card and that they have been installed within reach of the cables hanging from the back of the computer.
2. Plug the FireWire cable into your FireWire card.
3. Plug the pink microphone cable into the microphone port on your system.
4. Plug the green speaker cable into the speaker port on your system.

Powering Your Computer

1. Make sure that the red voltage indicator at the back of your computer is in the proper position (115V for North America and 230V for most European countries).
2. Plug one end of the power cord into the computer and the other into an available wall socket.

Contents

This package should contain:

- 1 x ATX8300PRO2/ATX8300PRO2B professional series mid-tower computer case with 300 Watt 12V ATX power supply and case fan
- 1 x power cord
- Assorted screws

Requirements

This case does **not** include any hard or floppy disk drives, motherboards, sound cards, USB/FireWire cards or any other computer component not listed above. You will need to supply these components yourself. The front USB, sound, and FireWire ports require a host controller (not included) to operate properly.

Assembling Your Computer

NOTE: This section is intended as a guide only. When installing computer components, be sure to refer to the manufacturer's installation documentation before attempting to install the parts.

Removing the Cover from Your Case

1. Make sure that the case is not plugged in and that you are properly grounded.
2. Gently lay the case on its right side.
3. Simultaneously pull the two green tabs upwards and slide the panel back then lift off towards you so it is entirely removed from the case.

Closing Your Case

1. Turn the panel so that the two tabs are aligned with the back of the computer.
2. Gently slide the panel into the case until it clicks into place. Make sure that the ridge on the back of the panel is properly aligned with the computer case. When the panel is correctly in place, it will be flush with the rest of the case and can not be removed without unlocking the tabs.

Installing Your Motherboard

NOTE: Please refer to your motherboard manufacturer's installation procedures to ensure proper installation of your motherboard.

1. Open your case using the procedure described on page 3.
2. If your motherboard comes with an input/output panel (the collection of ports on the back of your system) that is different than the panel provided by StarTech.com, remove the StarTech.com input/output panel by firmly pressing it from the outside until it pops free. Insert the new input/output panel according to the manufacturer's instructions.
3. Align the motherboard so that the slots and ports on the board line up with the card brackets and input/output panel along the back of the computer. Make note of and mark the holes in the case that line up with holes in the motherboard.
4. Screw your motherboard to the holes in the case making sure you have a non-metallic washer (not provided) between the screws and the motherboard.
5. Connect the power supply to the motherboard as directed by your motherboard manufacturer.
6. Attach the labeled LED connectors to your motherboard as directed by your motherboard manufacturer.
7. Connect your labelled USB 2.0 plugs to your motherboard according to motherboard manufacturer's specifications.
8. Attach the cables from the rear fan to your motherboard's main fan or exhaust fan as indicated in your motherboard manufacturer's manual.

Installing Your Floppy and CD Drives

NOTE: Please refer to your disk drive manufacturer's installation procedures to ensure proper installation of the drive.

Depending on the size of your floppy disk drive, you will install it in either the 3.5" bays located just below the hard disk drive, or the 5.25" bays located near the top of the case. Your CD drive will be installed in one of the 5.25" drive bays.

1. Remove the front plastic bay cover of the case.
2. Beneath the plastic bay cover will be a thin plate of metal that has been perforated around the edges. Remove this plate by working it back and forth until it completely snaps off.
3. Make sure that the green-handled floppy latch above the corresponding drive bay is in the "Unlocked" position. When unlocked, the arrow on the drive locking mechanism will be lined up with the arrow beside the locked icon. (The locked/unlocked icons are etched onto the locking mechanism above the green tabs)
4. Slide the disk drive into place, making sure that it is flush with the front panel of the computer and that the screw hole on the disk drive lines up with the hole in the bay.

5. Move the green-handled floppy latch into the "Locked" position to secure the drive.

NOTE: If you are going to be moving the computer case, StarTech.com recommends securing the disk drive with a screw to prevent damage.

6. Connect your disk drive to your motherboard and power supply as directed in their respective installation guides.
7. Repeat Steps 1 to 6 for any other disk drives you want to install in their respective 5.25" or 3.5" bays.

Installing a Hard Disk Drive

NOTE: Please refer to your hard disk drive manufacturer's installation procedures to ensure proper installation of the drive.

The hard disk drive bracket is the smaller grey removable bracket located below the 3.5" drive bays.

1. Remove the hard disk drive bracket by pushing down on the green tab and firmly pulling the bracket away from the case.
2. Slide your hard disk drive into the bracket, making sure that the screw holes on the hard disk are aligned with the circular screw holes in the bracket.
3. Screw the hard disk drive to the bracket.
4. Return the hard disk bracket to the computer case by aligning the bracket with the grooves in the case and gently sliding the bracket forward until it clicks.
5. Connect your hard disk drive to your motherboard and power supply as directed in their respective installation guides.

Removing the Expansion Slot Panel

You will need to remove an expansion slot panel on the back of your computer when you want to add a FireWire card, sound card, etc. to your computer.

1. Remove the silver expansion slot holder by pulling firmly upward on the green tab.
2. Remove one of the grey expansion slot covers by sliding it upwards until it is clear of the computer case.
3. Install your expansion card as directed by the manufacturer.
4. Repeat Steps 2 and 3 for any other expansion cards you wish to install.

NOTE: If you are going to be moving the computer case, StarTech.com recommends securing the expansion slot holder with a screw to prevent damage.

5. Replace the slot holder, making sure it clicks into place.