

TUXEDO TOUCH™

SECURITY AND HOME/BUSINESS CONTROLLER



Honeywell's Tuxedo Touch is a 7", high-resolution graphic touchscreen and controller that integrates security with home and business automation. It provides opportunities to capture new prospects and markets by seamlessly integrating security with voice commands, video viewing and recording, and the ability to control Z-Wave® enabled thermostats, lights, locks and shades. This versatile product is the perfect way to differentiate your business and safeguard your accounts.

Consumers can now utilize groundbreaking voice control in everyday living. By speaking commands such as "leaving the house" or "returning home", users can perform a range of tasks, such as arming their systems, adjusting Z-Wave enabled thermostats, controlling lights, locking doors and more.

With Honeywell Total Connect™ Remote Services, users can also view cameras, control their security system, lights, locks and thermostats, and receive event-driven email and video alerts remotely—a great opportunity for additional RMR.

FEATURES

- Centralized control of:
 - Security system
 - Video cameras
 - Z-Wave enabled devices: thermostats, lights, locks, shades
- Built-in web server allows for local control of the system through any Wi-Fi® enabled device (smartphone, iPad®, iPhone®, PC, Internet TV, etc.)
- Built-in Z-Wave controller allows for 232 Z-Wave devices (check compatibility chart for specific devices)
- Connect up to 32 MPEG4, H.264 or OnVIF format IP cameras and view up to four cameras directly on the Tuxedo Touch display or locally on Wi-Fi enabled devices (check compatibility chart for specified cameras)
- Supports Honeywell's low-light IP camera (iPCAM-WL) that allows for a better viewing experience in low light and dark areas
- Control system devices and actions by speaking specific voice commands
 - Wake Up
 - Bed Time
 - Leaving The House
 - Returning Home
 - Evening
 - Cameras
- Remote software updates can automatically be sent to any field-installed Tuxedo Touch controllers connected to the Internet
- Video viewing and recording
 - Record two-minute videos from any system camera and view right on the Tuxedo Touch display or Wi-Fi enabled devices (15 seconds pre-event and 1:45 post event)
 - Recording can be done manually or set as a scene to activate based on a specific day, time or event
 - Recording capacity is based on size of the SD card
- 7" widescreen color display
 - 16M colors and 800 x 480 resolution
- Customize up to 30 scenes to have system devices act based on time, day or system events
- Sunset/Sunrise – Scenes automatically update based on sunset/sunrise times/changes
- Group similar devices (all locks, all cameras, etc.) to reduce programming time and complexity when creating customized scenes
- Option for Wi-Fi or Cat5/Ethernet to connect to the premises LAN
- Supports VISTA Intelligent Programming (VIP)
- View local weather directly on the Tuxedo Touch controller
- Available in two colors (white and silver)
- Embedded sales and training videos
 - Tuxedo Touch sales video
 - Programming Z-Wave devices
 - Programming Z-Wave scenes
 - How to use web server for local Wi-Fi enabled devices
 - How to customize homescreen for dealer, digital picture frame and video viewer
 - How to install and program IP cameras
- Honeywell Total Connect Remote Services compatible
- Visit the Tuxedo Touch™ dealer toolkit at <http://www.tuxedotouchtoolkit.com/> for more information about the following:
 - All compatible Z-Wave devices
 - All compatible IP cameras
 - All compatible tablets/Wi-Fi enabled devices
 - Training videos
 - Sales/introductory videos
 - Product literature and images
 - Latest software revision for manual downloading

TUXEDO TOUCH™

SECURITY AND HOME/BUSINESS CONTROLLER

FEATURES

Compatibility

Control Panel	Max. No. of Tuxedo Touch Home/Business Controllers
VISTA®-15P/FA148CP	2
VISTA-15PSIA/FA148CPSIA	2
VISTA-20P/FA168CPS	4
VISTA-20PSIA/FA168CPSSIA	4
VISTA-21iP	4
VISTA-21iPSIA	4
VISTA-128BPE/FA1660CE	3
VISTA-128SIAE	3
VISTA-128BPT/FA1660CT	6
VISTA-128BPTSIA	6
VISTA-128FBP/FA1670C	3
VISTA-250BPE	3
VISTA-250FBP/FA1700C	3
VISTA-250BPT	6
VISTA-32FBPT	6
VISTA-128FBPT/FA1670CT	6
VISTA-250FBPT/FA1700CT	6

Agency Listings

UL 365 – Police Station Connected Burglar Alarm Units and Systems

UL 609 – Local Burglar Alarm Units and Systems

UL 985 – Household Fire Warning System Units

UL 1023 – Household Burglar Alarm System Units

UL 1610 – Central Station Burglar Alarm Units

ANSI/SIA CP-01-2010 – Control Panel Standard, Features for False Alarm Reduction

CAN/ULC-S303-M91 – Local Burglar Alarm Units and Systems

CAN/ULC-S304-06 – Signal Receiving Centre and Premise Burglar Alarm Control Units

ULC-S545-02 – Residential Fire Warning System Control Units

ULC/ORD-C1023-74 – Household Burglar Alarm System Units

SPECIFICATIONS

Physical

8.23" W x 5.59" H x 1.13" D
(21.90 cm W x 14.20 cm H x 2.87 cm D)

Wiring

(Standard four-wire connection)

Black Ground
Red +12VDC (Aux Power)
Green "Data in" to control panel
Yellow "Data out" from control panel

Current Draw

Backlight OFF, Sound OFF – 12V, 140mA
Backlight ON, Sound OFF – 12V, 225mA
Backlight ON, Sound ON – 12V, 260mA

ORDERING

TUXWIFIW	Color Graphic Voice Touchscreen Security Keypad and Home/Business Controller with Integrated Wi-Fi® (White)
TUXWIFIS	Color Graphic Voice Touchscreen Security Keypad and Home/Business Controller with Integrated Wi-Fi (Silver)
ZWSTAT	Z-Wave® Thermostat
iPCAM-WL	Wired/Wireless Indoor Low-Light IP Camera (White)
iPCAM-WI2/B	Wired/Wireless IP Camera (White/Black)
iPCAM-WO	Wired/Wireless Outdoor IP Camera (White)
WG-1103 (CM)/WG-3103 (CMP)	Genesis Series Cable (Standard Four-wire Connection)
WG-1133 (FT4)/WG-3103 (FT6)	Genesis Series Cable (Standard Four-wire Connection) – Canada

For more information: www.honeywell.com/security

Automation and Control Solutions

Honeywell Security Products Americas
2 Corporate Center Dr. Suite 100
P.O. Box 9040
Melville, NY 11747
1.800.467.5875
www.honeywell.com