

**20606**

## **INSTALLATION INSTRUCTIONS**

Please read carefully and save these instructions as you may need them a later date.

### **CAUTION**

**WARNING:** Risk of Fire. Consult a qualified electrician to ensure correct branch circuit conductor.

Turn off the main power at the circuit breaker before installing the fixture in order to prevent possible shock.

### **GENERAL**

All electrical connections must be in accordance with local and National Electrical Code (N.E.C.) standards. If you are unfamiliar with proper electrical wiring connections obtain the services of a qualified electrician.

Remove the fixture and the mounting package from the box and make sure that no parts are missing by referencing the illustration.

### **ASSEMBLY AND INSTALLATION**

1. Thread the center tube (2) onto the support bracket of shade (3), and then thread the socket assembly (1) onto the center tube (2).
2. Screw the loop (4) onto the support bracket of shade (3). Attach one end of the quick link (5) with chain to the loop (4). Weave fixture wires through chain links, skipping every other chain link, the canopy loop ring (6), canopy loop (7) and canopy (8) into the junction box.
3. Attach the mounting bar (10) with box screws (9) to the outlet box.
4. Pull out the outlet wire and ground wire from the outlet box.  
Make wire connections with wire nut (11).  
--Connect the ribbed wire w/o marking (Neutral wire) or white wire from the light to the white wire from power source.  
--Connect the wire with the markings and smooth surface (Live wire) or black wire from the light to the black wire from power source.  
--Wrap the grounding wire (green wire or bare copper wire) from the light around the green screw on the mounting bar (10), then connect it to the grounding conductor from power source.
5. Screw the canopy loop (7) onto the mounting bar (10), Attach the fixture canopy (8) to the outlet box by tightening the canopy loop ring (6) onto the canopy loop (7).
6. Install six 60W Max. B10 bulbs: (bulbs not included)  
(Don't exceed the maximum capacity recommended on the sockets).

