



## 2-Way Wireless Outdoor Siren WT8911



Make some noise. In combination with DSC's 2-Way Wireless Security Suite, the WT8911 Outdoor Siren is the Sound Choice

### Greater Protection. Complete Security.

How would you like to offer your customers a security system that provides complete security via a host of devices, including keypads, sirens, detectors and wireless keys, and also supports GSM and IP communications – all of it wirelessly? The new DSC's 2-Way Wireless Security Suite delivers just that...and so much more.

### The Best Defence is a Good Offence

The WT8911 Wireless Outdoor Siren is a fully supervised wireless siren designed to work with the ALEXOR Wireless Panel. The WT8911 combines form and function to provide improved protection against intruders, before they get the chance to enter the home. With its powerful 100dB sounder, the WT8911 will announce unwanted entrance to property and premises. The accompanying strobe light also provides a visual warning and deterrent upon activation. The WT8911 distinguishes between burglar and fire alarm by emitting different sounds for each and indicates arm and disarm squawks.

### Build Your Brand and Your Business

The WT8911 siren can be installed anywhere outdoors (or even indoors, for those requiring a louder siren) fast and easy. A large surface area on the siren allows for security company logos, increasing brand presence and awareness.

### Secure, Continuous Communication with Added Benefits

The WT8911 offers 2-way wireless and continuously supervised communication with the ALEXOR Wireless Panel. The signals between the WT8911 and the panel are fully encrypted, prohibiting unauthorized interruption of communication between the two. If the WT8911 siren is disabled or tampered with, ALEXOR will immediately be signaled and the appropriate transmission will



**868** MHz

instantly be transmitted to the monitoring station. Additionally, one of the other sirens (either indoor or outdoor or ALEXOR's onboard siren itself) installed on the system will make up for the absence of the WT8911. Up to four sirens can be installed on the ALEXOR Wireless Panel.

An added benefit is that an onboard temperature sensor provides the current outdoor temperature to the accompanying WT5500-868 wire-free keypad display (also part of DSC's 2-Way Wireless Security Suite).



**Product features**

- Reliable 868 MHz technology
- Siren output is 100dB
- Siren sounds for: Alarms & Squawks
- Strobe light functionality to visually indicate alarms
- Provides outdoor temperature reading to the WT5500-868 wireless keypad
- Transmits module status including tamper and low battery
- Fully supervised
- Case and wall tamper
- Up to 4 sirens per system
- Large print area for company logo
- IP34 rating

**Compatibility**

868 MHz Alexor Wireless Panel

**Specifications**

Dimensions .....	280 mm× 216 mm× 46mm (11"× 8.5"× 1.8")
Weight .....	820g (1.8 lbs)
Output .....	100 dB
Battery .....	1 "D" cell Lithium
Battery Life .....	2-3 years (typical usage)
Wireless Range .....	300m/984ft Nominal Open Air
Operating Environment .....	-35° to 70°C (-31° to 158°F)
Relative Humidity .....	5% to 95%

PN 30001153 R001