

# Lamp AS-R / Charger Options


## [Technical Description]

### Product Description

Dedicated range of chargers for AS-R rechargeable flashlight, featuring:

- Options for charging and storing 1, 3, 4, 5 or up to 40 lamps at a time. One charger, one power plug!
- Verification of battery status, automatic disconnection to avoid overcharge
- Charge indicating red/green LED
- Robust housing with safe lamp connection. Easy to mount on walls, in fire stations and vehicles.

### Product Views



AS-R Lamp in charge position



Individual Charger block



3 lamps charger



40 lamps charger


### Technical specifications

| Specification             | Description   |
|---------------------------|---|
| <b>Power Supply</b>       | European net adapter 100/240V AC 50/60Hz<br>Vehicle battery 12V DC , cable with 2A or 3A fuse<br>Vehicle battery 24V DC , cable with DC 24/12 converter |
| <b>Charging duration</b>  | Approx. 5 hours   |
| <b>Weight</b>             | Approx. 200g per charger block, net adapter: 125g   |
| <b>Dimensions [LxWxH]</b> | 1 lamp charger : 100x102x38 mm<br>3 lamps charger: 270x102x38 mm<br>5 lamps charger: 440x102x38 mm<br>40 lamps charger: 970x880x70 mm                   |

### Approvals

| Specification    | Description   | Approvals                |
|------------------|---|--------------------------|
| <b>Markings</b>  | - According to Directive 72/245/EEC (95/54/EC) on radio interferences in emergency vehicles | CE Marking<br>e9 Marking |
| <b>IP Rating</b> | - Limited protection from liquid splash   | IP54                     |

## Ordering Information

| Standard Versions  | Part Number                          | Description   |
|--|--------------------------------------|---|
|         | GA1483-A                             | Individual charger for Lamp AS-R, 240V  |
|  | GA1483-B                             | 3-Lamps charger for Lamp AS-R, 240V   |
|  | GA1483-C                             | 5-Lamps charger for Lamp AS-R, 240V   |
| <b>Further versions</b><br><br><b>Minimum quantities and longer leadtimes may apply.</b> | GA1483-D                             | 40-lamp charger, Lamp AS-R, 240V connector  |
|  | GA1483-M                             | Individual charger for Lamp AS-R, 100-240V connector Multicountry (UK and others) |
|  | GA1483-E                             | Individual charger for Lamp AS-R, 12V connector                                   |
|  | GA1483-F                             | 3-lamp charger, for Lamp AS-R, 12V connector                                      |
|  | GA1483-X                             | 4-lamp charger, for Lamp AS-R, 12V connector                                      |
|  | GA1483-G                             | 5-lamp charger, for Lamp AS-R, 12V connector                                      |
|  | GA1483-I                             | Individual charger, for Lamp AS-R, 24V connector                                  |
|  | GA1483-J                             | 3-lamp charger, for Lamp AS-R, 24V connector                                      |
|  | GA1483-Y                             | 4-lamp charger, for Lamp AS-R, 24V connector                                      |
|  | GA1483-K (charger with 2 connectors) | 5-lamp charger, for Lamp AS-R, 24V connector                                      |
| <b>Packaging</b>   | Individual carton boxes              |   |
| <b>Warranty</b>  |                                      |   |
| Lamp chargers are covered by a two years warranty.                                       |                                      |   |