



## VISTA-128FBPT

### VISTA® Commercial Partitioned Fire and Burglary Alarm Control Panel

The VISTA-128FBPT provides the ultimate protection for life and property. This commercial fire and burglary control panel supports up to eight partitions and up to 128 zones/points using hardwired, wireless and V-Plex® addressable technologies. A diverse line of Honeywell Home initiating devices, notification appliances, communication devices, keypads, RF receivers and relays satisfy a wide range of installation requirements.

The VISTA-128FBPT control is suitable for fire-only applications, as well as for installations requiring integrated fire/burglary systems. It is the perfect solution for medical and professional office buildings, churches



and synagogues, banks, schools, strip malls, and factory or warehouse environments.

VISTA-128FBPT is compatible with a number of AlarmNet® communication products for alarm reporting, uploading/downloading and Resideo Total Connect Remote Services.

## FEATURES

- Eight hardwired zones standard, expandable to 120 V-Plex addressable points/zones or 128 wireless points/zones
- Supports up to 128 wireless zones (fewer if using hardwired and/or V-Plex zones)
- Can control eight separate areas independently (8 partitions)
- Common lobby partition – auto arm or disarm based upon assigned partitions
- Master partition – used for viewing status of all partitions
- Supports commercial wireless fire and burglary devices
- Stores up to 512 events
- Accommodates 150 user codes and up to 250 access card holders using VISTAKEY®
- Supports V-Plex addressable VISTAKEY access control (1 to 8 doors)
- Two on-board NACS delivering a total of 2.3A @ 12V
- Automatic smoke detector sensitivity maintenance testing\*
- Four-wire smoke reset using on-board Form C relay
- Supports Dynamic Signaling for AlarmNet® Communicators
- Supports Internet and GSM alarm reporting
- Supports graphical user interfaces for burglary use (e.g. 6280 and Tuxedo Touch™)
- Supports 6160CR-2 multi-LED fire keypad
- Upload/download via AlarmNet® Communicators
- Carbon monoxide (CO) zone support
- On-board serial port for communication with WIN-PAK®, Pro-Watch® and approved third-party applications
- Supports Total Connect Remote Services\*

\* Event reporting only for fire partition.

# VISTA-128FBPT

## VISTA® Commercial Partitioned Fire and Burglary Alarm Control Panel

### ADDITIONAL FEATURES

---

- **Notification Appliance Circuits (two):**
  - Programmable
  - Individually silenceable
- **False alarm reduction features:**
  - Exit error logic
  - Exit delay reset
  - Cross zoning
  - Call waiting defeat
  - Recent close report
- **Supports commercial hardwired, addressable V-Plex® polling loop and wireless zones**
- **Hardwired zones**
  - Provides eight style B hardwired zones
  - EOLR supervised for Fire and UL burglary installations
  - Supports N.O. or N.C sensors
  - Individually assignable to any of eight partitions (all fire zones on partition 1)
  - Up to 16 two-wire smoke detectors each on zone one and two (32 total)
- **Patented addressable V-Plex polling loop technology**
  - Class B, Style 3 SLC
  - Supports 120 two-wire addressable points
  - Global polling technology for faster processing
  - Supervised by panel
  - Zones individually assignable to partitions, notification circuit (bell) output or auxiliary relay
  - 4,000 ft. capability without the use of shielded cable
  - Extender/Isolation bus modules
  - Eight zone - Class A and B expander module
  - Eight zone - Class B expander module
  - Single-zone supervised contact module
  - Single relay module for auxiliary fire functions
  - Supports anti-masking feature on "smart" motion detectors (e.g. DT7500SN)
- **UL Listed wireless expansion**
  - Supports up to 128 wireless zones/points
  - Supervised by control for check-in signals
  - Tamper protection for transmitters Individually assignable up to eight partitions
  - Supports commercial wireless smoke detectors
- **Up to eight doors using VISTAKEY® V-Plex Access Control**
- **Event reporting**
- **Local printer for event log printing**
- **Communication**
  - Phone line, GSM and IP communicator support
  - Panel operation during download
  - Four or 10-digit subscriber account numbers
- **Extra security feature that requires master code to allow installer into program mode (enabled through Compass Downloader)**

# VISTA-128FBPT

## VISTA® Commercial Partitioned Fire and Burglary Alarm Control Panel

### SPECIFICATIONS

---

#### Electrical:

**Primary power:** 18VAC @ 72VA  
Honeywell Home No. 1451-UL9

**Control panel quiescent current draw:** 300mA

**Backup battery:**  
12VDC, 12AH min to 34.4AH max  
Lead acid battery (gel type)

**Alarm power:** 12VDC, 1.7A max  
for each notification (bell) circuit  
output Total 2.3A 12V

**Aux. standby pwr:** 12VDC, 1A max

**Total power:** 2.3A at 12VDC

**Standby time:** 24 hours with 1A  
standby load using 34.4AH battery

**Fusing:** Battery input, aux. and  
notification (bell) circuit outputs are  
protected using PTC circuit protectors.  
All outputs are power limited.

#### Optional 24-volt kit

#### Communications

##### Dialer:

**Line seize:** Double Pole

**Ringer equiv:** 0.7B

**Formats:** ADEMCO® Low Speed,  
ADEMCO 4+2 Express, ADEMCO  
High Speed, ADEMCO Contact ID,  
Sescoa and Radionics

#### Backup Communication:

Dual phone line capability using  
5140DLM module

#### AlarmNet® Communicators:

GSM, i-GSM and IP Communicators

#### Cabinet Dimensions:

18" H x 14.5" W x 4.3"D

#### Environmental:

**Storage temp:** 14°F to 158°F  
(-10°C to 70°C)

**Operating temp:** 32°F to 122°F  
(0°C to 50°C)

**Humidity:** 85% RH

**EMI:** Meets or exceeds the following  
requirements:

- FCC Part 15, Class B Device

- FCC Part 68

- IEC EMC Directive

#### Agency Listings:

UL864/NFPA72 Local, Central  
Station and Remote Station

ULC-S559-04 – Equipment for Fire  
Signal Receiving Centers and Systems

UL1076 – Proprietary Burglar Alarm  
Units and Systems

UL1610 – Central Station Burglar  
Alarm Units

CAN/ULC-S304-06 – Signal Receiving  
Centre and Premise Burglar Alarm  
Control Units

UL1635 – Digital Alarm Communicator  
System Units

UL365 – Police Station Connected  
Burglar Alarm Units and Systems

UL609 – Local Burglar Alarm Units and  
Systems

UL985 – Household Fire Warning  
System Units

UL1023 – Household Burglar Alarm  
System Units

ULC-S545-02 – Residential Fire  
Warning System Control Units

ULC/ORD-C1023-74 – Preliminary  
Standard for Household Burglar Alarm  
System Units

ULC-S303-M91 – Standard for Local  
Burglar Alarm Units and Systems

Factory Mutual (FM)

California State Fire Marshal (CSFM)

FDNY Certificate #6140

# VISTA-128FBPT

## VISTA® Commercial Partitioned Fire and Burglary Alarm Control Panel

### COMPATIBLE DEVICES

#### Auxiliary Devices

- 6160CR-2 – Red Fire Keypad
- 6160 – Burglary Keypad
- 6280, Tuxedo Touch™, Tuxedo Touch with Wi-Fi® Graphic Keypads – Burglary
- 4204 – Relay Module, four Form C contacts
- 4204CF – Two supervised NAC circuits
- 5881ENHC Series RF receivers
- 5883H RF receiver
- 6220S – System printer

#### Two-Wire Smoke Detectors Conventional

- System Sensor
- ESL
- DSC

#### Horn/Strobes

- System Sensor
- Wheelock
- Gentex

#### Manual Pull Stations

- 5140MPS-1
- 5140MPS-2

#### V-Plex (Addressable) Devices

- 4208U Universal Eight-zone Expansion Module
- 4208EX Universal Eight-zone Expansion Module (Canada)
- 4208SN Eight-zone Expansion Module
- 4101SN Single Relay/Zone Module
- 4208SNF Class A/B Expander Module

- 4190SN Remote Point Module - two zones
- 4193SN and 4193SNP Two-zone Expander Modules

#### V-Plex Extender/Isolation Modules

- 4297 Extender/Isolator Module
- VSI Isolator Module

#### V-Plex Smoke Detectors

- 5193SD
- 5193SDT
- 5193SDTA

#### V-Plex Passive Infrared Detectors

- IS2500SN
- DT7500SN

#### V-Plex (Addressable) Contacts

- 4939SN-WH
- 4959SN

#### V-Plex Glassbreak Detectors

- FG1625SN

#### Seismic Detectors

- SC100
- SC105

#### Commercial Wireless Devices

- 5808W3/5808W3A- Photoelectric Smoke/Heat Detector
- 5806W3 - Photoelectric Smoke Detector
- 5809 - Wireless Heat Detector
- 5817CB - Wireless Commercial Transmitter
- 5869 - Hold-Up Transmitter

- 5800CO/5800COA – Carbon Monoxide Detector
- 5800PIR-COM – Commercial PIR

#### Access Control

- VISTAKEY® V-Plex (addressable) Access Control
- VISTAKEY-SK Starter Kit
- VISTAKEY-EX Expansion Kit
- Integrates with WIN-PAK® and Pro-Watch® systems

#### Alarm Communications

##### U.S.

- GSMV4G – Digital Cellular Communicator with Two-way Voice Transport Capability
- iGSMV/iGSMV4G – Internet and Digital Cellular Communicator
- iGSMCF/iGSMCFP4G – Commercial Fire Digital Cellular Communicator with Internet
- iGSMHS/iGSMHS4G – High Security Internet and Digital Cellular Communicator
- 7845i-ENT – Internet/Intranet Enterprise Communicator
- 7847i – Internet Communicator

##### Canada

- GSMV4GCN – Digital Cellular Communicator with Two-way Voice Transport Capability
- iGSMVCN/iGSMVCN4G – Internet and Digital Cellular Communicator

Product specifications subject to change.

### ORDERING

V128FBPT	Commercial Fire and Partitioned Burglary Alarm Control Panel 12V Model
V128FBPT24KT (U.S. Only)	Commercial Fire and Partitioned Burglary Alarm Control Panel with External 24V Power Supply (6A, four outputs, synchronized)

#### For more information

security.honeywellhome.com



#### Resideo Technologies, Inc.

2 Corporate Center Drive, Suite 100  
P.O. Box 9040  
Melville, NY 11747  
1-800-645-7492  
resideo.com

All trademarks are property of their respective owners.

L/VS128FBPTD/D | 11/19  
© 2019 Resideo Technologies, Inc.  
This product is manufactured by Resideo and its affiliates. The Honeywell Home trademark is used under license from Honeywell International Inc. All rights reserved.

**Honeywell Home**