



Professional Smart Security

BAT-Connect Communicator

Models: BAT-CONNECT-V, BAT-CONNECT-A

BAT-Connect is engineered for professional security dealers and integrators who want the most versatile communicator on the market. The universal dual-path communicator can be used with most hardwired or hybrid panels. LTE-M cellular technology and automatic panel detection allows alarm dealers to complete more installations and skip the next cellular sunset.

Offer a modern interactive experience on new and existing systems with the Alula Smart Security app. Customers can arm and disarm the system, view cameras, control smart devices and initiate scenes right from their phones or the Slimline Touchpad PRO interface.



alula.com/bat-connect

» **Works with most panels**

You'll always have the right part for the job with this universal communicator

» **Saves money**

Equipped with LTE-M technology so you can skip the 4G sunset

» **Eliminates service hassles**

Remote programming, troubleshooting, and over-the-air firmware updates will fix most issues

» **Faster and easier installations**

Automatic panel detection and zone configuration means less work for you

» **Ensures peace of mind**

Never lose a signal with IP and cellular connectivity

» **Unleashes RMR potential**

Increase attachment rates by offering smart phone control, cameras and system automation capabilities

Technical Specifications

Physical	
Housing Dimensions	8.5 x 5.0 x 1.3 in
Weight	10 oz
Mounting Fasteners	#6 screws and wall anchors (included)
Cover Securing Screw	#4 screw (included)
Device	
Reported Indications	Cover tamper, Wall tamper
Current Draw	100mA (Nominal)
Input Voltage	9-14V DC
Environmental	
Operating Temperature	32° F to 120° F
Maximum Humidity	85% non-condensing relative humidity
Communications	
Cell	Yes
Ethernet	Yes
Wi-Fi	Yes, local network
Models	
BAT-CONNECT-V (Verizon), BAT-CONNECT-A (AT&T)	
Regulatory	
FCC, IC	

Compatibility

Honeywell	DSC	Interlogix	NAPCO
Vista 15p	PC1616	NX-4/NX-4V2	GEM P800
Vista 20p	PC1832	NX-6/NX-6V2	GEM P801
Vista 21ip	PC1864	NX-8/NX-8V2	GEM P816
First Alert FA148CP	PC5020	NX-8E	GEM P1632
First Alert FA168CP	PC580	Concord 4	
Safewatch Pro 3000	PC1555/1555MX PC5010		

Tip and ring support for all Contact ID panels including:

Honeywell: Vista 10p, 15p, 20, 128

DSC: Alexor, Impassa, Neo

Interlogix/GE: Concord 2, 3 Express