

# Manual Screw Plug Adapter

Model:  
POE-CON02

KARBON<sup>vision</sup>

## Features

Connect two male RJ45 to your switch, then remotely connect each male RJ45 to your camera, WIFI or phone. Use any CAT5e cable between the two devices.

- It provides a low cost solution for either use case.
- UPoE operation is intended for use with PoE Switch devices. Ethernet doubler operation is intended for use with any 10/100 switch with or without PoE.
- Save the Cables, Tubes cost. And Save the installation cost and Time.

Use with a injector to double the power into one device from 30 watts to 60 watts- Combines two 802.3at /af ports into one uPOE port.

Supports gigabit data rates and 60 watts per CAT-6 cable.

Use two for each UPOE device-one on the PoE side and one on the LAN side of a PoE Switch devices.

Use to put two 10/100 ethernet circuits onto one long run ethernet cable with or without PoE.

supports 2 individual 10/100 data rate connections and up to 30 watts for each(60watts total) on CAT5e.

## Product image



## Applicable scope

CCTV Camera, AP, wifi



## Parameters Table

Model Number	POE-CON02
Power sources	PoE switch or injetor
8 wires, 4 Pair split 10/100 Connector	Female RJ45
4 wires, 2 Pair split 10/100 Connector	male RJ45 with 1&2 and 3&6
Input voltage Max	up to 57V
Input Current at 48V	65Ma per pair-60 Watts total
Operating Temp	0°C~50°C
Size	125mm Cable Length