

# PRCP2

## PrimeChime Plus 2®

### Product Description

The PrimeChime Plus 2® keeps all the popular features of NICOR's PrimeChime Plus® electronic doorbell with added compatibility with most video doorbell buttons. The PRCP2 combines both line voltage and low voltage into a single unit and offers a paintable, screwless faceplate for simple installation and a seamless look. Separate ring tones for front and rear doors allows you to keep track of exactly which door to answer. NICOR's lighted button makes your doorbell easily visible to visitors at all times of day, welcoming them to your home.

#### Construction

- ABS Housing
- Combines line voltage and low voltage in a single unit
- Screwless ABS Faceplate
- Two-wire pigtail for line voltage input
- Multiple poke-in connectors for low voltage output for front and back doorbells

#### Electrical

- Integrated transformer
- Input: 120VAC/60Hz
- Output: 20VAC
- Digital control board with speaker
- Two distinct chime tones: Westminster for front and Ding-Dong for rear door.

#### Finish

- Matte White
- Faceplate is field paintable

#### Installation

- Includes two lighted rectangle doorbell buttons
- Compatible with many popular video doorbell buttons  
*(see compatibility list and/or test for compatibility before installation)*
- Installs quickly into a standard two-gang dual-voltage wall box
- Daisy chain one additional PrimeChime Plus 2® unit (max 100ft total wire length)\*
- Doorbell buttons connect with 18ga-22ga solid wire (max 100ft distance)
- For installations where higher power surge may be possible, NICOR recommends installing additional surge protection at the electrical distribution panels

*\*each chime requires individual 120VAC input*

#### Warranty



- 1 year limited system warranty standard
- Warranty does not cover product failure due to an overvoltage event (power surge)

Project

Catalog

Type

Date



1.97 in  
(50 mm)



Patent Pending

## Accessories

PRCP2BUTTONDBBK	Lighted Decorative Button - Black
PRCP2BUTTONDBCO	Lighted Decorative Button - Copper
PRCP2BUTTONDBNK	Lighted Decorative Button - Nickel
PRCP2BUTTONDBWH	Lighted Decorative Button - White
PRCP2BUTTONSBAB	Lighted Stucco Button - Antique Brass
PRCP2BUTTONSBBZ	Lighted Stucco Button - Architectural Bronze
PRCP2BUTTONSBPB	Lighted Stucco Button - Polished Brass
PRCP2BUTTONSBNK	Lighted Stucco Button - Nickel
PRCP2BUTTONSBWH	Lighted Stucco Button - White

## Recommended Video Doorbell\*

Manufacturer	Model
Ring	Video Doorbell
	Video Doorbell 2
	Video Doorbell 3
	Video Doorbell 3 Plus
	Video Doorbell Pro
	Video Doorbell Elite
Google Nest	Hello
Skybell	Skybell HD

\*Not a complete list. Call NICOR or test for compatibility before installation.

## Ordering Information

Example: PRCP2

Series  
PRCP2

Specifications and dimensions subject to change without notice.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.