


CLASSIC HANGING LAMP



CROSS BAR WITH SET OF CHANDELIER FIXTURES



CANOPY



FIXTURE LOOPS

I INSTRUCTIONS

1. Carefully remove all parts from the box and remove the packaging materials that attached directly to the fixtures.
2. Before starting installation; turn off the power supply to the circuit where the chandelier is situated. Use a circuit tester to verify the power is off.
3. Starting the assembly; unscrew the fixture loops also loosen the Canopy on the on pipe nipple of the chandelier.
4. Using a ladder set the chandelier near the ceiling surface. After that, fasten the crossbar with the existing screw of the junction as illustrated on sketch.
5. Connect the ground wire from the fixture to the ground junction box wire and wrap the connection with electrical tape .Connect the hot wire to the hot junction box wire and wrap the connection with electrical tape. Connect the neutral wire to the neutral junction box wire and wrap the connection with electrical tape.
6. After doing the wiring fixtures, move the canopy against the ceiling surface and screw the fixture loops back to the pipe nipples.

REMINDER

If you are installing the chandelier in a dining room or kitchen, make sure the chandelier hangs at least 30 inches above any table. The chandelier's diameter should be at least 12 inches narrower than the width of the table.

