



Southwire™

Professional VDV Cable Mapper

M300P

QUICKLY TESTS VOICE, DATA AND VIDEO CABLING FOR COMMON WIRING FAULTS.



PORT COVERS
Protect RJ45 and RJ11
ports from dust and debris

EASY-TO-READ
LCD display with backlight

MAPS
Multiple cable runs with included
RJ45 & Coax "F" ID remotes
(5 of each are included)

RUGGED
double-molded housing
with snap-in remote

TONE GENERATOR
For cable tracking



Southwire™

TOOLS & EQUIPMENT

[BUILT FOR DURABILITY.
BUILT FOR RELIABILITY.
BUILT FOR WORK.]

1-855-SWT00LS
(855-798-6657)



Scan code to see more
Southwiretools.com



Southwire™

M300P

Professional VDV Cable Mapper



- EASY-TO-READ LCD DISPLAY WITH BACKLIGHT
- PORT COVERS PROTECT RJ45 AND RJ11 PORTS FROM DUST AND DEBRIS
- BUILT IN TONE GENERATOR FOR CABLE TRACING (SEPARATE AMPLIFIER PROBE REQUIRED)
- MAPS MULTIPLE CABLE RUNS WITH INCLUDED RJ45 & COAX "F" ID REMOTES (5 OF EACH ARE INCLUDED)
- TEST PATCH CABLES OR INSTALLED CABLES



Operating Temperature	32°F to 122°F (0°C to 50°C)
Storage Temperature	-4°F to 140°F (-20°C to 60°C)
Humidity	10% to 90%, non-condensing
Maximum Voltage between any two points without damage	60V DC or 55V AC
Batteries	One 9V Battery
Cable Types	Shielded or Unshielded: Cat 7, Cat 7a, Cat 6a, Cat 6, Cat 5e, Cat 5, Cat 4, Cat 3, Coax
Maximum Coax Cable Length	1000 feet (305m)
Minimum Cable Length for Split Pair Detection	1.6 feet (0.5m)
Maximum Coax Cable Resistance	100 ohms maximum DC
Dimensions	7.13" X 28.6" X 16.1" (18.1 X 7.3 X 4.1 cm)
Weight	0.78lb (353g)

INCLUDES

Professional VDV Cable Mapper, ID Remote Kit with 5 RJ45 and 5 Coax Remotes, 9V Battery



Southwire™

TOOLS & EQUIPMENT

[BUILT FOR DURABILITY.
BUILT FOR RELIABILITY.
BUILT FOR WORK.]

1-855-SWT00LS
(855-798-6657)



Scan code to see more

Southwiretools.com