



CPS750AI Power Inverter

Offering household power on the go.

The CyberPower 750AI Inverter converts 12v DC automobile power to standard 120v AC home power - up to 750 watts. Simply attach the unit directly to a 12V battery with the supplied clamps.

It is equipped with two (2) 120v outlets for running multiple devices at the same time, and also has a convenient USB port for charging cell phones, MP3 players, and digital cameras.

It has full-time surge protection that guards against power fluctuations caused by vehicle startup and shutdown, and has an ergonomic design and small foot print. It's the perfect device to power all your mobile/consumer electronics, small appliances, emergency equipment, and portable tools.

A Two-Year Warranty ensures that this product has passed our highest quality standards in design, assembly, material and workmanship.

Typical Applications

- Tablets
- Laptops
- Smartphones

Features

- 750 Watt DC-to-AC Inverter
- 2 x 120V AC plug
- On-board USB device charger
- GFCI shock protection
- All outlets surge protected
- Status LED indicators
- 2-Year Warranty

CPS750AI Power Inverter

Offering household power on the go.

GENERAL	
Product Type	Power Inverter
INPUT	
Voltage	10.5Vdc ~ 15.5Vdc
Plug Type	12Vdc Auto Power Port & Battery Clamp
OUTPUT	
Watts - Continuous	750
Watts - Peak	750
Watts - Surge	1500
On Battery Voltage	120Vac ± 10%
On Battery Frequency	60Hz
Outlets - Total	2
Outlet Type	NEMA 5-15R
USB Charge Port - Total	1
USB Charging Amperage	1.0A
Efficiency	> 85%
PHYSICAL	
Color	Black/Gray
Enclosure Construction	ABS
Dimensions (WxHxD) (in.)	1 x 3.25 x 6
CERTIFICATIONS	
Environmental	RoHS Compliant
WARRANTY	
Product Warranty	2 Years Limited