



## CPS1000AI Power Inverter

Offering household power on the go.

The CyberPower 1000AI Inverter converts 12v DC automobile power to standard 120v AC home power - up to 1000 watts. It is equipped with 2 (two) 120v outlets for running multiple devices at the same time, and also has a convenient USB port for charging cell phones, MP3 players, and digital cameras.

The 1000AI also features Remote Control Connectivity (optional) so the device can be controlled from an auxiliary location. It has full-time surge protection that guards against power fluctuations caused by vehicle startup and shutdown, and has an ergonomic design with a rugged frame for easy and convenient mounting. The Status LED indicators give a heads-up display of the current load that is connected to the device. It's the perfect device to power all your small appliances, emergency equipment, and portable tools.

A Two-Year Warranty ensures that this product has passed our highest quality standards in design, assembly, material and workmanship.

### Typical Applications

- Tablets
- Laptops
- Smartphones

### Features

- 750 Watt DC-to-AC Inverter
- 2 x 120V AC plug
- On-board USB device charger
- GFCI shock protection
- All outlets surge protected
- Status LED indicators
- 2-Year Warranty

# CPS1000AI Power Inverter

Offering household power on the go.

GENERAL	
Product Type	Power Inverter
INPUT	
Voltage	10.5Vdc ~ 15.5Vdc
Plug Type	12Vdc Wire Terminals
OUTPUT	
Watts - Continuous	1000
Watts - Peak	1000
Watts - Surge	2000
On Battery Voltage	120Vac ± 10%
On Battery Frequency	60Hz
Outlets - Total	2
Outlet Type	NEMA 5-15R
USB Charge Port - Total	1
USB Charging Amperage	1.0A
Efficiency	> 85%
PHYSICAL	
Color	Black/Gray
Enclosure Construction	ABS
Dimensions (WxHxD) (in.)	9.5 x 7.25 x 3.25
CERTIFICATIONS	
Environmental	RoHS Compliant
WARRANTY	
Product Warranty	2 Years Limited