# **USER'S MANUAL**

CHX12D

12" (305 mm) DUAL 4 $\Omega$  VOICE COIL SUBWOOFER



BOSS Audio Systems 3451 Lunar Court • Oxnard, CA 93030

www.bossaudio.com 800-999-1236 US Toll-free 805-751-4853 Customer Service

Tech Support: www.bossaudio.com/support/technical-support



0418

# **USER'S MANUAL**

# CHX12D

12" (305 mm) DUAL  $4\Omega$  VOICE COIL SUBWOOFER







Congratulations on your purchase of the Boss Audio Chaos Series Subwoofer. Boss Audio takes great pride in producing products that look great, sound great and stand up to the daily rigors applied by audio enthusiasts around the world.





CHX12D 12" (30 cm) Subwoofer

- Dual  $4\Omega$  Voice Coils
- 2600 W Peak Power Handling
- High Temperature Voice Coils








## Wiring your Subwoofer



### **Multiple Subwoofers**





## **Products Specifications**

Impedance	Dual 4Ω
Resonant Frequency	35 Hz
Qts	0.534
Qms	3.18
Qes	0.642

Vas 2.447 ft<sup>3</sup> (69.3 liters)

Xmax 11 mm Sensitivity (1 W/ 1 m) 88.6 dB Peak Power Handling 2600 W

Mounting Depth 6.02" (153 mm)
Cutout Diameter 11" (280 mm)





3



#### **Enclosures**


The CHX12D is designed to work in both sealed or ported enclosures,

Since the woofer has pole-vent, it needs a minimum clearance from the rear wall enclosure of 0.75" (19 mm).

Below you will find the dimensions to make the enclosure, it has been designed for maximum output while retaining great sound quality.


The dimensions have already accounted for the volume displacement of the subwoofer, and using 3/4" (19mm) MDF. All dimensions are external.

#### **Enclosures Dimensions**



#### **Sealed Dimensions:**

Length (L): 17" (432 mm) Width (W): 10" (254 mm) Height (H): 14" (356 mm) Cutout Diameter: 11" (280mm) Minimum Int. Volume: 1.2 ft<sup>3</sup>



#### **Ported Dimensions:**

Length (L): 16" (407mm) Width (W): 17.25" (438 mm) Height (H): 13.75" (349 mm) Port Width: 1.25" (32 mm) Port Height: 11" (280 mm) Port Length: 26" (661 mm) Port Extension: 11" (280 mm)

Tuning Freq: 36 Hz

Minimum Int. Volume: 1.5 ft<sup>3</sup>

5



#### **Technical Support**

If you need technical support with your Boss Audio product or have questions about it's use, please contact us:

805.751.4853 www.BossAudio.com

Due to ongoing product development, specifications are subject to change without notice.



