



PTE-1 REX (Request to Exit) switch

Description

The new PTE-1 exit switch connects to any 12V access controller and provides users FAST SIMPLE door egress. It's small, lightweight, IP68-waterproof and has a simple Red/Green LED so users can see it's status. PTE-1 is included in ZKAccess door kits and can be purchased separately, as well.

Specification

• Dimensions: 114Lx70Wx16H(mm)

Voltage: 12-24V

• Current: Standby 30mA, Operation: 70mA

• Output Contact: NO/NC/COM

Current Rating: 1A @ 30VDC 0.5A @ 125VDC

• Waterproof Level: IP-68

• LED Status: Red: Standby, Green: Operation

 Wire color: Red: Positive, Black: Negative, Yellow: NC, White: COM, Green: NO

Wiring Diagram





6 Kingsbridge Road, Unit 8, Fairfield, NJ 07004 Phone: (862) 505-2101 • Fax: (862) 204-5906 • sales@zkaccess.com • www.zkaccess.com

