Product data sheet

Specifications



Motor Starter, TeSys NEMA, nonreversing, Size 0, 18A, 3 pole, HP rated, Motor Logic SSOLR, 120 VAC 60 Hz coil, open

T36BN13G7

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Product	Starter
Range of Product	TeSys N
Current Rating	18 A
Certifications	UL Listed CSA
Control Circuit Type	Common control circuit
Enclosure Type	Not rated (open device)
Auxiliary Contacts	1 NO + 1 NC
Horsepower Rating	3 HP 200 V AC 3 HP 230 V AC 5 HP 460 V AC 5 HP 575 V AC
Number of Poles	3P
Phase	3 phase
Maximum Voltage Rating	600 V AC
NEMA Size	0
Control Circuit Voltage	120 V AC
Starter Type	Non reversing
Electrical Connection	Screw clamp terminals
Overload Type	Solid state Motor Logic class 10/20 6…18 A

Ordering and shipping details

Category	US10CP121198
Discount Schedule	0CP1
GTIN	785901990284
Returnability	Yes
Country of origin	US

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	8.000 in (20.320 cm)
Package 1 Width	10.000 in (25.400 cm)

Price is “List Price” and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Package 1 Length	10.000 in (25.400 cm)
Package weight(Lbs)	2.930 lb(US) (1.329 kg)

Contractual warranty

Warranty (in months)	18

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

Use Better

Materials and Substances

Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant By Exemption

Use Again

Repack and remanufacture

Take-back	No