

TRANSFORMER

0600SS

600W PRO-SERIES TRANSFORMER
600W TRANSFORMER



DETAILS	
FINISH:	Stainless Steel
MATERIAL:	Stainless Steel
DIMMABLE:	YES - WITH MLV ON TRANSFORMER PRIMARY

DIMENSIONS	
WIDTH:	7.8"
HEIGHT:	17.3"
DEPTH:	5.8
WEIGHT:	22lb

LIGHT SOURCE	
VOLTAGE:	120v

SHIPPING	
CARTON LENGTH:	7.5
CARTON WIDTH:	20
CARTON HEIGHT:	6
CARTON WEIGHT:	24



HINKLEY TRANSFORMERS

COMPATIBLE WITH SMART TECHNOLOGY

<p style="text-align: center; font-weight: bold; font-size: small;">SMART HOME AUTOMATION KITS</p> <p style="font-size: x-small;">Lutron Caseta Legrand Samsung Smart Things Insteon</p>	<p style="text-align: center; font-weight: bold; font-size: small;">OUTDOOR SMART SWITCH DEVICES</p> <p style="font-size: x-small;">GE Wink Plug In TP-Links Smart Plug</p>
--	---

COMPATIBLE WITH OTHER MLV-TYPE CONTROLS

SELECTING A TRANSFORMER

INCANDESCENT (DESCRIPTION, HALOGEN)	LED
$\left(\text{Number of Fixtures} \times \text{Fixture Wattage} \right) \cdot .20\%$ <p style="font-size: x-small; text-align: center;">Minimum Wattage * Transformer Requirement</p>	$\left(\text{Number of Fixtures} \times \text{Fixture VA} \right) \cdot .20\%$ <p style="font-size: x-small; text-align: center;">Minimum VA * Transformer Requirement</p>
SELECT PROPER TRANSFORMER FROM ABOVE CALCULATION	

PRODUCT DETAILS:

- Wet Rated
- The Hinkley Home Automation App allows you to control your landscape lights anytime, anywhere. You can turn dimmers on/off and adjust sliding brightness settings remotely.
- A modular timer and photocell are available
- Pro Series Transformers carry a lifetime warranty
- This design is made with stainless steel for superior strength and performance
- Line voltage fixture that accommodates higher wattage and light output (ideal for commercial and public spaces)
- Solid stainless steel is designed for superior strength and performance
- Use to convert 120V household voltage to 12V for low voltage landscape lighting