


## 19in Vertical Wall Mount Rack Bracket

### Product IDs

- RK119WALLV2
- RK219WALLV
- RK319WALLV2
- RK419WALLV2
- RK519WALLV
- RK619WALLV

### Product Diagram



Component	Function <small>*Product may vary from image</small>
1 Mounting Rails	• Features <b>Square Cage Nut Holes</b> to mount the equipment
2 Wall Bracket	• <b>Mounting Holes</b> along the <b>Wall Bracket</b> are used to <b>Fasten</b> it to a <b>Wall</b>

### Package Contents

- Wall-Mount Bracket x 1
- Wood Screws x 6
- Quick-Start Guide x 1

Product ID	M5 Square Cage Nuts Quantity	M5 Screws Quantity
RK119WALLV2	x 4	x 4
RK219WALLV	x 8	x 8
RK319WALLV2	x 12	x 12
RK419WALLV2	x 16	x 16
RK519WALLV	x 16	x 16
RK619WALLV	x 16	x 16

### Requirements

For the latest manuals, product information, technical specifications, and declarations of conformance, please visit:

[www.StarTech.com/RK119WALLV2](http://www.StarTech.com/RK119WALLV2)

[www.StarTech.com/RK219WALLV](http://www.StarTech.com/RK219WALLV)

[www.StarTech.com/RK319WALLV2](http://www.StarTech.com/RK319WALLV2)

[www.StarTech.com/RK419WALLV2](http://www.StarTech.com/RK419WALLV2)

[www.StarTech.com/RK519WALLV](http://www.StarTech.com/RK519WALLV)

[www.StarTech.com/RK619WALLV](http://www.StarTech.com/RK619WALLV)

- Appropriate mounting hardware for the wall or surface type
- Phillips head screwdriver
- Cage nut tool (Optional)

#### Warnings!

*Read the entire Quick-Start Guide and ensure the instructions are fully understood before assembling and/or using this product.*

*Before adding equipment to this product, ensure this product has been properly mounted.*

*Never operate this product if parts are missing or damaged.*

*The mounting hardware included with this product might not be adequate for some wall or mounting structures. If lacking the necessary expertise to mount this product, contact a construction professional to install the Wall Rack Bracket or to provide specific mounting instructions for the wall structure.*

*Ensure the weight of the equipment does not exceed the weight capacity of this product. If the weight capacity is exceeded, personal injury or damage to the equipment are possibilities. These products can support the following weight: 130 lb (59 kg) for RK119WALLV2, 125.3 lb (56.7 kg) for RK219WALLV, 150lb (68 kg) for RK319WALLV2, 180 lb (81.6 Kg) for RK419WALLV2, 198.9 lb (90 kg) for RK519WALLV, and 200.5 lb (90.7 kg) for RK619WALLV.*

*Ensure the type of wall structure and mounting hardware will properly support the mounted equipment. Failure to do so might result in personal injury and/or equipment damage. The wall or mounting structure should be capable of supporting at least four times the weight of the mounted equipment.*

## Installation

### Mount the Rack Bracket

The mounting holes are spaced 16 inches (2 inner holes) and 18.8 inches (4 outer holes) apart. Test fit the Rack Bracket on the surface to ensure proper fit on the designated location.

1. Mark the **Mounting Points** (x6) using the **Mounting Holes** (x6) on the **Wall Bracket** as a **Template**.
2. Use the **Wood Screws** (x6) to fasten the **Wall Bracket** to the **Mounting Surface**.  
*The included screws are for wood surfaces only.*
3. Install the **M5 Square Cage Nuts** onto the desired **Square Cage Nut Holes** where the **Equipment** will be installed. Use a **Cage Nut Tool** if available or your preferred installation method.
4. Use a **Phillips Head Screwdriver** to install the **M5 Screws** and secure the **Equipment** onto the **Mounting Rails**.

### Regulatory Compliance

#### Use of Trademarks, Registered Trademarks, and other Protected Names and Symbols

This manual may make reference to trademarks, registered trademarks, and other protected names and/or symbols of third-party companies not related in any way to StarTech.com. Where they occur these references are for illustrative purposes only and do not represent an endorsement of a product or service by StarTech.com, or an endorsement of the product(s) to which this manual applies by the third-party company in question. StarTech.com hereby acknowledges that all trademarks, registered trademarks, service marks, and other protected names and/or symbols contained in this manual and related documents are the property of their respective holders.

PHILLIPS® is a registered trademark of Phillips Screw Company in the United States or other countries.

### Warranty Information

This product is backed by a lifetime warranty.

For further information on product warranty terms and conditions, please refer to [www.startech.com/warranty](http://www.startech.com/warranty).

### Limitation of Liability

In no event shall the liability of StarTech.com Ltd. and StarTech.com USA LLP (or their officers, directors, employees or agents) for any damages (whether direct or indirect, special, punitive, incidental, consequential, or otherwise), loss of profits, loss of business, or any pecuniary loss, arising out of or related to the use of the product exceed the actual price paid for the product. Some states do not allow the exclusion or limitation of incidental or consequential damages. If such laws apply, the limitations or exclusions contained in this statement may not apply to you.

#### StarTech.com Ltd.

45 Artisans Crescent  
London, Ontario  
N5V 5E9  
Canada

#### StarTech.com LLP

4490 South Hamilton  
Road  
Groveport, Ohio  
43125  
U.S.A.

#### StarTech.com Ltd.

Unit B, Pinnacle 15  
Gowerton Road  
Brackmills,  
Northampton  
NN4 7BW  
United Kingdom

#### StarTech.com Ltd.

Siriusdreef 17-27  
2132 WT Hoofddorp  
The Netherlands

FR: [startech.com/fr](http://startech.com/fr)  
DE: [startech.com/de](http://startech.com/de)  
ES: [startech.com/es](http://startech.com/es)  
NL: [startech.com/nl](http://startech.com/nl)  
IT: [startech.com/it](http://startech.com/it)  
JP: [startech.com/jp](http://startech.com/jp)