

Product data sheet

Specifications

SQUARE D



Generator panel, QO, 1 phase, 18 spaces, 36 circuits, 30A main breaker, PoN, NEMA1, cover with door

QOGP3P3036P

Product availability: Stock - Normally stocked in distribution facility

Price*: 455.00 USD

Main

Marketing Trade Name	QO
Product Type	Panel

Complementary

Tightening Torque	Cover 20 lb.in
PoN Convertible Mains (lugs)	PoN Convertible Mains (breaker)
Rated Current	30 A
Max Short Circuit Current Rating	10 kA
Maximum Number of Single Pole Circuits	36
Number of Phases	1 phase
Voltage Rating	120/240 V AC
Ground Bar	Grounding bar (ordered separately)
Height	17.9 in (455 mm)
Width	14.3 in (362 mm)
Depth	3.7 in (95 mm)

Environment

Enclosure Rating	NEMA 1 indoor enclosure
Ambient Air Temperature for Operation	23 °F (-5 °C) 104 °F (40 °C)
Product Certifications	UL Listed

Ordering and shipping details

Category	US1DE3C00145
Discount Schedule	DE3C
GTIN	785901666967
Returnability	Yes
Country of origin	US

Packing Units

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	3.74 in (9.5 cm)
Package 1 Width	14.25 in (36.2 cm)
Package 1 Length	17.91 in (45.5 cm)
Package 1 Weight	20.501 lb(US) (9.299 kg)

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard

No

Packaging without single use plastic

No

California proposition 65

WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Again

Repack and remanufacture

Circularity Profile

No need of specific recycling operations

Take-back

No