



Transform any standard light switch into a connected wall switch and conveniently control lighting and accessories from anywhere.



WALL SWITCH KEY FEATURES



Standard Installation



Pull Out Tab



Remote Access



Voice Control



LED Night Light



No Hub Required



Two-Year Warranty

ACCESSORIES TO CONTROL WITH WALL SWITCH







Landscape Lighting



Ceiling Fans



Entry Lighting



Flush Mount Fixtures



Pendant Lighting



Exterior Lighting

COMPATIBLE PLATFORMS









SPECIAL ORDER CUSTOM COLORS AVAILABLE















WALL SWITCH FEATURES AND RATINGS

- Fits any standard gang box
- Supports single pole, 3- and 4-way operation
- No hub or running additional wires
- Compatible with most standard bulbs
- Works with any standard rocker faceplate
- Pull-out HomeKit[™] pairing tab
- Customizable LED night light
- Input: 120-277VAC, 50/60Hz

• Output: 120-277VAC, 50/60Hz

Resistive: 1800W @ 120-277VAC, 15A/6.5A

Tungsten: 960W @ 120VAC, 8ATungsten: 1800W @ 277VAC, 6.5A

• Ballast: 10A @ 277VAC

• Motor: 1HP @ 120 & 277VAC

CONNECTED APP

The iDevices Connected app allows you to control and schedule all your iDevices products from anywhere, with your iOS or Android™ device.

App Features:

- Voice control with Siri®, Alexa and the Google Assistant
- Access from anywhere, no hub required
- Set schedules, scenes, and control multiple homes
- Compatible with other HomeKit[™] products
- Customize with pictures of your home
- Over-the-air software updates









SHIPPING SPECIFICATIONS

	Shipping Specs	Product Dimensions	Carton Dimensions
Product Number	IDEV0008		
UPC#	852931005643		
Cube (FT3)	0.17		
Carton UPC#	10852931005640		
Height		4.35"	5.00"
Width		2.00"	5.5"
Depth		2.50"	10.5"
GW		6.4 oz	4.34 lbs
NW			4.06 lbs
Pack Quantity			10

STANDARDS & CERTIFICATIONS: UL compliant, FCC compliant, RoHS compliant, CSA compliant, IC compliant, Wi-Fi CERTIFIED™, Bluetooth®