

6150RF

Fixed Language Display Keypad with Integrated Wireless Transceiver

Add wireless technology to any installation with the 6150RF Fixed Language Display Keypad with Integrated Wireless Transceiver, which offers the unbeatable combination of attractive, convenient features and competitive value in a single, quick-install package. The integrated design solves even the trickiest installation challenges and reduces costs by letting you add full wireless capability to any compatible VISTA® control panel—without additional wiring or sacrificing zones.

Adding the 5828 or 5828V wireless keypad to a VISTA control panel system presents a tremendous up-sell opportunity and offers a secondary wireless keypad with reduced installation time.



With door



Without door

FEATURES

- 6150 Fixed Language Keypad
- Built-in 16-Zone wireless transceiver
- Compatible with 5828 and 5828V wireless keypads
- Single four-wire run required

The ideal choice for wireless keys:

- Keys can be programmed at the panel
- Keys can be enrolled locally at the keypad, without taking up additional zones at the control

- Fully compatible with all 5800 wireless devices including bi-directional
- On-board single relay provides a low cost solution for opening garage doors.

Stylish Design

- Sleek white design blends with any décor
- Contoured, removable door for desired keypad customization
- Smooth, unobtrusive appearance when the door is closed

Easy to Operate

- The fixed language display is easy to read, with large characters and simplified descriptions
- Sounder beeps to help identify security system status
- Comfortable soft-touch keys labeled with simple commands are illuminated for nighttime visibility
- Four function keys can be programmed for one touch operation and are accessible even when the door is closed

6150RF

Fixed Language Display Keypad with Integrated Wireless Transceiver

SPECIFICATIONS

DIMENSIONS

- 4-7/8" H x 6" W x 1" D
(125mm x 160mm x 25 mm)

SOUNDER

- Piezo Electric

WIRING

- - **(Black)**: Ground
- + **(Red)**: +12 VDC (Aux. Power)
- **D1 (Green)**: "Data In" to control panel
- **D0 (Yellow)**: "Data out" from control panel

CURRENT

- **Standby**: 80mA
- **Activated**: 105mA

OPERATING WIRELESS

- FREQUENCY:**
- 345 MHz

ORDERING

6150RF	Fixed Language Display Keypad with Integrated Wireless Transceiver - English (Honeywell Home)
6150RFC	Fixed Language Display Keypad with Integrated Wireless Transceiver - English (Resideo)
6150RFFR	Fixed Language Display Keypad with Integrated Wireless Transceiver - French (Honeywell Home)
6150RFFRC	Fixed Language Display Keypad with Integrated Wireless Transceiver - French (Resideo)
5828	Wireless Fixed English Display Keypad
5828V	Wireless Fixed English Display Keypad with Voice Annunciation and Message Center

For more information

www.resideo.com/pro



For more information
resideo.com

Resideo Technologies, Inc.
2 Corporate Center Drive,
Suite 100
P.O. Box 9040
Melville, NY 11747
1-800-645-7492

All trademarks are property
of their respective owners.

L/6150RFD/D | JC | 06/23
© 2023 Resideo Technologies, Inc.
All rights reserved.
The Honeywell Home trademark
is used under license from
Honeywell International Inc.
These products are manufactured
by Resideo Technologies, Inc.
and its affiliates.