Technical Details



REQUIREMENTS | **SPECIFICATIONS** | DOWNLOADS

POWER

Input / Output:	AC 100-240 V, 50/60 Hz
Australia:	max. 10 A / 2300 W
United Kingdom:	max. 13 A / 2900 W
U.S. & Canada:	AC 120 V, 60 Hz, max. 15 A / 1,800 W
Switzerland:	max. 10 A / 2500 W
Europe:	Rated Current: Max. 11 A / 2500 W
-	Incandescent Tungsten Lamp Load: Max. 1A / 240 W
-	Ambient Temperature: 0-35°C
-	Internal Fuse: 12.5 A
-	Relay switched of by software at more than 11 A current
-	Standby Power Consumption: < 1 W

COMPATIBILITY

Australia:	Type I sockets (AS 3112)
Europe:	Type E & F sockets, Type C & F appliances
United Kingdom:	Type G (BS 1363) sockets & appliances
U.S. & Canada:	Type B sockets, Type A & B appliances
Switzerland:	Type J sockets, Type C & J appliances

WIRELESS CONNECTION

Thread

DIMENSIONS

Australia:	77 x 77 x 60 mm
Europe:	56 x 56 x 79 mm
United Kingdom:	72 x 72 x 71 mm
U.S. & Canada:	2.8 x 1.5 x 2.4 /70 x 39 x 60 mm
Switzerland:	54 x 54 x 79 mm

IN THE BOX

Eve Energy, Quick Start Guide EU / US / CH / UK / AU