



#### Accessories

Deco and Stucco Buttons Available



White Nickel Copper Black



Antique Brass Architectural Bronze Polished Brass



Nickel White

#### 📍 Location

- Front Door
- Rear Door
- Gated Entry
- Residential
- Commercial

#### ★ Product Edge



- Compatible with Ring
- Installs Directly into Dual Voltage Box
- Daisy Chain
- Paintable Faceplate
- Front and Rear Chimes

#### + Options

- Deco Buttons: White, Nickel, Copper and Black options
- Stucco Buttons: Architectural Bronze, Antique Brass, Polished Brass, Nickel, and White options

# The Same Doorbell You Love with the Added Security You Need

The **PrimeChime® Plus** keeps all the popular features of NICOR's PrimeChime® electronic doorbell and now adds compatibility with video doorbell buttons. The PRCP1 combines both line voltage and low voltage into a single unit and offers a paintable, screwless faceplate for simple installation and a seamless look. Separate ring tones for front and rear doors allows you to keep track of exactly which door to answer. NICOR's lighted button makes your doorbell easily visible to visitors at all times of day, welcoming them to your home.



\*not compatible with Ring Pro®

## Features

### Construction

- ABS Housing
- Combines line voltage and low voltage in a single unit
- Screwless ABS Faceplate
- Two-wire pigtail for line voltage input
- Multiple poke-in connectors for low voltage output for front and rear doorbells

### Electrical

- Integrated transformer
- Input: 120VAC/60Hz
- Output: 18VAC
- Digital control board with speaker
- Two distinct chime tones for front (Westminster) and rear (Ding-Dong) doors

### Finish

- Matte White
- Faceplate is field paintable

### Installation

- Includes two lighted rectangle doorbell buttons
- Compatible with many popular video doorbell buttons (see compatibility list and/or test for compatibility before installation)
- Installs quickly into a standard two-gang dual-voltage wall box
- Daisy chain up to four PrimeChime® Plus units (max 200ft total wire length)
- Doorbell buttons connect with 18ga-22ga wire (max 200ft total wire length)

### Warranty

- 1 year limited system warranty standard
- Warranty does not cover product failure due to an overvoltage event (power surge)

Recommended Video Doorbell**	
Manufacturer	Model
Ring	Video Doorbell
	Video Doorbell 2
	Video Doorbell Elite

\*\*Not a complete list. Call NICOR or test for compatibility before installation.

LIT-PRCP-10PK  
20190904

