LSE LED Direct/Indirect Linear

Product Description

The Elara Architectural LED Direct/Indirect Linear is an edge lit luminaire designed for individual units or continuous runs in commercial indoor applications. The elegant fixture achieves a polished, modern appearance with its silver powder-coated, 20-gauge aluminum housing and fully-welded seams. White or custom powder coat options are also available. Elara's acrylic light guide with laser etched patterns enables a variety of light distributions to suit your application, and a 50/50 distribution comes standard. The fixture is easily suspended using four mount points for y-cable, and includes two y-cables with canopy covers. Elara is available in 4-foot or 8-foot lengths in either integral or remote driver configurations.

Construction

- Housing formed 20ga aluminum
- Fully welded seams
- Available in 4' and 8' lengths
- Designed for individual units or continuous runs

Optical System

- Edgelit LED design
- Acrylic light guide with laser etched patterns for a variety of distributions
- 50% direct 50% indirect distribution standard
- 80/20, 20/80 and 100 down distributions available

Electrical

- Available in Driver Integrated and Remote Power System configurations
- Remote Power fixture provided with 2 connector ports
- Efficiency greater than 105 lumens per watt
- Universal Input of 120-277V, designed for through wiring
- Driver delivers full range dimming via 0-10VDC
- Operating Temperature of 32° to 122°F (0°C to 50°C)
- 10kA Surge suppression standard on integral version
- For installations where higher power surge may be possible, NICOR recommends installing additional surge protection at the electrical distribution panels

Mounting

- Integral fewature for varying mounting styles
- Cable suspension kit available
- Pendant mount kit available
- Wall mount kit available
- Strut mount kit available
- Continuous run installation kit available


Finish

- Silver powder coat finish standard
- · White or custom powder coat options available

Lumen Maintenance

- TM-21 Calculated L70(12K) hours = 113,000
- TM-21 Calculated L90(12K) hours = 38,000

Type Date 48in (1219 mm) 96in (2438 mm) 48 in (1219 mm)









Catalog


Photometric Data


LSE 20/80 3500K

120-277
40.7
4413
108.5
3406
85
133.0°
141.4°
1.42
1.56

Length Multiplier

8 Foot	1.98
Remote Drive	er Multiplier
LSE-1-***-R	0.989






CCT Data Multiplier			
LSE-1-4-2-U-40	1.020		
LSE-1-4-2-U-50	1.041		

Con	e of Light Tabulatio	n
Mounted height (Feet)	Footcandles Beam Center	Beam Width
4	53.8	5.9
6	23.9	8.9
8	13.5	11.9
10	8.6	14.9
12	6.0	17.8
14	4.4	20.8
16	3.4	23.8

Z	onal Lumen Summ	ary
Zone	Lumens	% of Luminaire
0-30	727	16.5%
0-40	1254	24.4%
0-60	2466	55.9%
0-90	3330	75.5%
90-180	1083	24.5%
0-180	4413	100.0%

LSE 50/50 3500K

Input Voltage (VAC)	120-277
System Level Power (W)	40.7
Delivered Lumens (Lm)	4413
System Efficacy (Lm/W)	108.5
Correlated Color Temp (K)	3406
Color Rendering Index (CRI)	85
Beam Angle 0-180°	139.5°
Beam Angle 90-270°	148.2°
Spacing Criteria 0°	1.50
Spacing Criteria 90°	1.70



Intensity Summary (Candle Power)			
Angle	0° Along	90° Across	
0	532	532	
15	535	555	
30	528	593	
45	491	595	
60	385	491	
75	190	243	
90	4	3	
105	229	331	
120	377	556	
135	400	514	
150	378	432	
165	375	390	
180	372	372	

Con	e of Light Tabulatio	n
Mounted height (Feet)	Footcandles Beam Center	Beam Width
4	33.3	6.4
6	14.8	9.6
8	8.3	12.8
10	5.3	16.0
12	3.7	19.2
14	2.7	22.4
16	2.1	25.6

	Zonal Lumen Summary	
Zone	Lumens	% of Luminaire
0-30	444	10.5%
 0-40	781	18.5%
0-60	1595	37.7%
0-90	2210	52.3%
90-180	2017	47.7%
0-180	4413	100.0%

Length Multiplier 8 Foot 1.98 Remote Driver Multiplier LSE-1-***-R 0.989

LSE 80/20 3500K

Input Voltage (VAC)	120-277
System Level Power (W)	40.7
Delivered Lumens (Lm)	4413
System Efficacy (Lm/W)	108.5
Correlated Color Temp (K)	3406
Color Rendering Index (CRI)	85
Beam Angle 0-180°	133.0°
Beam Angle 90-270°	141.4°
Spacing Criteria 0°	1.42
Spacing Criteria 90°	1.56

Length Multiplier		
8 Foot	1.98	
Remote Driver Multiplier		
LSE-1-***-R	0.989	

892 669 223	A T
	Ŧ

	Angle	0° Along	90° Across
	0	384	384
	15	371	367
4	30	328	320
	45	260	244
1	60	174	155
ł	75	81	62
	90	3	2
	105	263	319
	120	263	319
	135	727	842
	150	817	892
	165	857	877
	180	862	862
	ССТ	Data Mult	iplier
	LSE-1-4	-2-U-35	0.97

LSE-1-4-2-U-50

LSE-1-4-2-U-40

LSE-1-4-2-U-50

1.020

1.041

1.30

Con	e of Light Tabulatio	n
Mounted height (Feet)	Footcandles Beam Center	Beam Width
4	53.8	5.9
6	23.9	8.9
8	13.5	11.9
10	8.6	14.9
12	6.0	17.8
14	4.4	20.8
16	3.4	23.8

7	onal Lumen Summ	ary
Zone	Lumens	% of Luminaire
0-30	225	5.1%
0-40	402	9.1%
0-60	786	17.8%
0-90	1081	24.5%
90-180	3332	75.5%
0-180	4413	100.0%

Fixture tested per LM-79-08. Photometric data is of the performance of a representative fixture. Results may vary in the field.



	Integral Performa	ance Data	
Model Number	Lumens	Watts	Lumens/Watt
LSE-1-4-2-U-35	4413	40.7	108.5
LSE-1-4-2-U-40	4501	40.7	110.7
LSE-1-4-2-U-50	4594	40.7	113.0
LSE-1-8-2-U-35	8738	81.3	107.5
LSE-1-8-2-U-40	8911	81.3	109.6
LSE-1-8-2-U-50	9096	81.3	111.9
LSE-1-4-5-U-35	4413	40.7	108.5
LSE-1-4-5-U-40	4501	40.7	110.7
LSE-1-4-5-U-50	4594	40.7	113.0
LSE-1-8-5-U-35	8738	81.3	107.5
LSE-1-8-5-U-40	8911	81.3	109.6
LSE-1-8-5-U-50	9096	81.3	111.9
LSE-1-4-8-U-35	4413	40.7	108.5
LSE-1-4-8-U-40	4501	40.7	110.7
LSE-1-4-8-U-50	4594	40.7	113.0
LSE-1-8-8-U-35	8738	81.3	107.5
LSE-1-8-8-U-40	8911	81.3	109.6
LSE-1-8-8-U-50	9096	81.3	111.9
LSE-1-4-D-U-35	4413	40.7	108.5
LSE-1-4-D-U-40	4501	40.7	110.7
LSE-1-4-D-U-50	4594	40.7	113.0
LSE-1-8-D-U-35	8738	81.3	107.5
LSE-1-8-D-U-40	8911	81.3	109.6
LSE-1-8-D-U-50	9096	81.3	111.9

	LCU System	m Data	
Model Number	Lumens	Watts	Lumens/Watt
LSE-1-4-2-U-35	4364		
LSE-1-4-2-U-40	4451	Wattage based on LCU performance	Greater than 105 lm/w
LSE-1-4-2-U-50	4543		
LSE-1-8-2-U-35	8642		
LSE-1-8-2-U-40	8813	Wattage based on LCU performance	Greater than 105 lm/w
LSE-1-8-2-U-50	8996		
LSE-1-4-5-U-35	4364		
LSE-1-4-5-U-40	4451	Wattage based on LCU performance	Greater than 105 lm/w
LSE-1-4-5-U-50	4543		
LSE-1-8-5-U-35	8642		
LSE-1-8-5-U-40	8813	Wattage based on LCU performance	Greater than 105 lm/w
LSE-1-8-5-U-50	8996		
LSE-1-4-8-U-35	4364		
LSE-1-4-8-U-40	4451	Wattage based on LCU performance	Greater than 105 lm/w
LSE-1-4-8-U-50	4543		
LSE-1-8-8-U-35	8642		
LSE-1-8-8-U-40	8813	Wattage based on LCU performance	Greater than 105 lm/w
LSE-1-8-8-U-50	8996		
LSE-1-4-D-U-35	4364		
LSE-1-4-D-U-40	4451	Wattage based on LCU performance	Greater than 105 lm/w
LSE-1-4-D-U-50	4543		
LSE-1-8-D-U-35	8642		
LSE-1-8-D-U-40	8813	Wattage based on LCU performance	Greater than 105 lm/w
LSE-1-8-D-U-50	8996		

Orde	ring Infor	mation				Exc	Example: LSE-1-8-5-U-40-W-W	
Series	Version	Length	Distribution Pattern	Input Voltage	сст	Finish Color	Driver Configuration	
LSE	1 (Version 1)	4	2 (20 Up/80 Down)	U (120-277)	35 (3500 K)	S (Silver)	l (Integral)	
		8	5 (50 Up/50 Down)		40 (4000 K)	W (White)	W (Remote 18/2)*	
			8 (80 Up/20 Down)		50 (5000 K)	C (Custom)		
			D (100 Down)					

Specifications and dimensions subject to change without notice *Remote configuration requires installation of the Remote Power System

Accessories	Accessories sold separately	
LCU REMOTE POWER SYSTEM FOR LSE4		LCU2UNV54LSE4W
LCU REMOTE POWER SYSTEM FOR LSE8		LCU2UNV75LSE8W
LSA, LSE, LSQ PENDANT MOUNT, NON PO	WER FEED, 48" LENGTH	LSALSELSQ1PENDANT
LSA, LSE, LSQ PENDANT MOUNT, POWER	FEED, 48" LENGTH	LSALSELSQ1PENDANTPF
LSA, LSE, LSQ REMOTE PENDANT MOUNT	, NON POWER FEED, 48" LENGTH	LSALSELSQ1PENDANTRPF
LSE WALL MOUNT BRACKET (available on 4)	ít fixture only)	LSE-1-WALL
LSE, LSQ WALL MOUNT KIT POWER FEED		LSELSQ-1-WALL-PF
LSE AIRCRAFT CABLE KIT, NON POWER FE	ED, 150" LENGTH	LSE-1-CABLE
LSE AIRCRAFT CABLE KIT, POWER FEED, 1	50″ LENGTH	LSE-1-CABLE-PF
LSE REMOTE AIRCRAFT CABLE KIT, NON F	OWER FEED, 150" LENGTH	LSE-1-CABLE-R-PF
LSE CONTINUOUS RUN BRACKET		LSE-1-CR-BRACKET
LSE STRUT MOUNT KIT (threaded rod supplie	d by others)	LSE-1-STRUT

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

NICOR, Inc. 2200 Midtown Place NE, Albuquerque, NM 87107 P: 800.821.6283 F: 800.892.8393 www.nicorlighting.com December 23, 2022 12:27 PM rev 1.0

