



PRIME CHIME VERSION COMPARISON

	PRMC	PRCP2	EDC
			
SIZE (HxWxD)"	4.65 x 3.15 x 1.81	5.0 x 4.75 x 1.97	4.65 x 3.15 x 1.70
VIDEO DOORBELL COMPATIBILITY	Max connected video doorbells ALC SightHD (AWF71D) Alarm.com VB770 Amcrest AD110 Arlo Aud1001 Blink BDM00200UW Eufy T8210 Felt Smart Video Doorbell FIRST ALERT Google Nest Wired Remo+ Remo Bell S Ring 1 Ring 2 Ring 3 Ring 4 Ring Elite Ring Pro Ring Pro 2 Simply Safe SSDB3 Skybell Skybell HD Wyze Video Doorbell v2	Remo+ Remo Bell S Ring 1 Ring 2 Ring 3 Ring 4 Ring Elite Ring Pro Ring Pro 2 Simply Safe SSDB3 Skybell Skybell HD Wyze Video Doorbell v2 ALC SightHD (AWF71D) Alarm.com VB770 Amcrest AD110 Arlo Aud1001 Blink BDM00200UW Eufy T8210 Felt Smart Video Doorbell FIRST ALERT Google Nest Wired	Not compatible
MAX CONNECTED VIDEO DOORBELLS	2	1	0
INPUT	120VAC/60Hz	120VAC/60Hz	120VAC/60Hz
INTEGRATED TRANSFORMER	Yes	Yes	Yes
TRANSFORMER OUTPUT	24VAC, 16W	20VAC, 12W	5VDC, 2W
INSTALLATION METHOD	Recessed Single Gang Box	Line/Low Voltage Recessed Double Gang Box	Recessed Single Gang Box
CHIME METHOD	Digital	Digital	Digital
DAISY CHAIN COMPATIBLE	Yes, up to 10	Yes, up to 2	Yes, up to 4